X Input Device Extension Library

Mark Patrick, Ardent Computer
George Sachs
Hewlett-Packard

X Input Device Extension Library

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

Table of Contents

Chapter 1. Input Extension

Overview

[illegible]

Design Approach

[illegible]

Core Input Devices

[illegible]

[illegible]

[illegible] (`KeyPress`, `KeyRelease`, `ButtonPress`, `ButtonRelease`, `MotionNotify`) [illegible]

[illegible]

Extension Input Devices

[illegible]

[illegible] DeviceKeyPress, DeviceKeyRelease, DeviceButtonPress, DeviceButtonRelease, DeviceMotionNotify, [illegible]

[illegible]

[illegible]

[illegible]

[illegible]

Input Device Classes

[illegible]

[illegible]	[illegible]
[illegible]	[illegible]
[illegible]	[illegible]
[illegible]	[illegible]
[illegible]	[illegible]
[illegible]	[illegible]

[illegible] XListInputDevices [illegible]

[illegible]

Using Extension Input Devices

[illegible]

- `XListInputDevices` [illegible] `XListInputDevices` [illegible]
- `XOpenDevice` [illegible] `XDevice` [illegible] `XOpenDevice` [illegible]
- [illegible] `DeviceKeyPress` [illegible]
- `XSelectExtensionEvent` [illegible] `XSelectExtensionEvent` [illegible]
- `XNextEvent` [illegible] `XNextEvent` [illegible]

[illegible]

Library Extension Requests

[illegible] `<X11/extensions/XI.h>` [illegible] `<X11/extensions/XInput.h>` [illegible]

[illegible] `NoSuchExtension` [illegible]

[illegible]

Window Manager Functions

[illegible]

- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]

Changing the Core Devices

[illegible]

[illegible]

[illegible] `ChangeDeviceNotify` [illegible]

[illegible] `XChangeDeviceNotify` [illegible] `MappingNotify` [illegible]

[illegible] `AlreadyGrabbed` [illegible] `GrabFrozen` [illegible]

[illegible] `BadDevice` [illegible] `XOpenDevice` [illegible]

[illegible] `ChangeDevice` [illegible]

[illegible] XCloseDevice [illegible] BadDevice [illegible]

[illegible] XChangeKeyboardDevice [illegible] Keys [illegible] ListInputDevices [illegible] BadMatch [illegible]

```
int   XChangeKeyboardDevice( *display,   *device);
```

[illegible]

[illegible]

[illegible] XChangeKeyboardDevice [illegible] Success [illegible] ChangeDeviceNotify [illegible] NewKeyboard [illegible] MappingNotify [illegible] MappingKeyboard [illegible]

XChangeKeyboardDevice [illegible] AlreadyGrabbed, BadDevice, BadMatch, [illegible] GrabFrozen [illegible]

[illegible] XChangePointerDevice [illegible] Valuators [illegible] XListInputDevices [illegible] BadMatch [illegible]

[illegible] BadDevice [illegible]

```
int   XChangePointerDevice( *display,   *device,   xaxis,   yaxis);
```

[illegible]

[illegible]

[illegible]

[illegible]

[illegible] XChangePointerDevice [illegible] Success [illegible] ChangeDeviceNotify [illegible] NewPointer [illegible] MappingNotify [illegible] MappingPointer [illegible]

XChangePointerDevice [illegible] AlreadyGrabbed, BadDevice, BadMatch, [illegible] GrabFrozen [illegible]

Event Synchronization and Core Grabs

[illegible]

[illegible] XGrabPointer [illegible] XGrabButton [illegible] XGrabKeyboard [illegible] XGrabKey [illegible]

Extension Active Grabs

[illegible] XGrabDevice [illegible] XGrabKeyboard [illegible] XUngrabDevice [illegible]

[illegible] XGrabDeviceButton [illegible] XGrabDeviceKey [illegible] XUngrabDeviceKey [illegible] XUngrabDeviceButton [illegible]

[illegible] XGrabDevice [illegible] XOpenDevice [illegible]

```
int   XGrabDevice( *display,   *device,   grab_window,   owner_events,
event_count,    *event_list,    this_device_mode,    other_device_mode,
time);
```

- -

[illegible]

[illegible]

[illegible]

[illegible] True [illegible] False .

[illegible]

[illegible]

[illegible] GrabModeSync [illegible] GrabModeAsync .

[illegible] GrabModeSync [illegible] GrabModeAsync .

[illegible] CurrentTime .

XGrabDevice [illegible] DeviceFocusIn [illegible] DeviceFocusOut [illegible]

[illegible] False [illegible] True [illegible]

[illegible]

- [illegible] GrabModeAsync [illegible] GrabModeSync [illegible] XAllowDeviceEvents [illegible]
- [illegible] GrabModeAsync [illegible] GrabModeSync [illegible] XAllowEvents [illegible] XAllowDeviceEvents [illegible]

XGrabDevice [illegible]

- [illegible] AlreadyGrabbed .
- [illegible] GrabNotViewable .
- [illegible] GrabInvalidTime . [illegible] CurrentTime [illegible]
- [illegible] GrabFrozen .

[illegible]

[illegible]

`XGrabDevice` [illegible] `BadClass`, [illegible] `BadDevice`, [illegible] `BadValue`, [illegible] `BadWindow` [illegible]

[illegible] `XUngrabDevice` [illegible]

```
int   XUngrabDevice( *display,  *device,  time);
```

[illegible]

[illegible]

[illegible] `CurrentTime`.

`XUngrabDevice` [illegible] `XGrabDevice` [illegible] `XGrabDeviceKey`. [illegible] `XUngrabDevice` [illegible] `DeviceFocusIn` [illegible] `DeviceFocusOut` [illegible] `XUngrabDevice` [illegible]

`XUngrabDevice` [illegible] `BadDevice` [illegible]

Passively Grabbing a Key

[illegible] `XGrabDeviceKey`. [illegible] `XOpenDevice` [illegible] `BadDevice` [illegible] `Keys`, [illegible] `BadMatch` [illegible]

```
int     XGrabDeviceKey( *display,     *device,     keycode,     modi-
fiers,  *modifier_device,  grab_window,  owner_events,  event_count,
*event_list,  this_device_mode,  other_device_mode);
```

[illegible]

[illegible]

[illegible] `AnyKey`.

[illegible] `ShiftMask`, `LockMask`, `ControlMask`, `Mod1Mask`, `Mod2Mask`, `Mod3Mask`, `Mod4Mask`, [illegible] `Mod5Mask`.

[illegible] `AnyModifier`, [illegible]

[illegible]

[illegible]

[illegible] True [illegible] False .

[illegible]

[illegible]

[illegible] GrabModeSync [illegible] GrabModeAsync .

[illegible] GrabModeSync [illegible] GrabModeAsync .

XGrabDeviceKey [illegible] XGrabKey [illegible] XGrabDeviceKey [illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible] XGrabDevice , [illegible] DeviceKeyPress [illegible] DeviceKeyPress [illegible]

[illegible] XGrabDevice . [illegible]

[illegible]

[illegible] AnyModifier [illegible] AnyKey [illegible] XListInputDevices [illegible] XGrabDeviceKey [illegible] BadValue [illegible]

XGrabDeviceKey BadAccess * ' ' + ' ' ' ! <) AnyModifier AnyKey , G) * ' $ + BadAccess * * * ' !

XGrabDeviceKey) Success)$) *) '$ * G) !

XGrabDeviceKey BadAccess , BadClass , BadDevice , BadMatch , BadValue , BadWindow !

8 $ + * . XUngrabDeviceKey .

`int XUngrabDeviceKey( *display, *device, keycode, modifiers, *modifier_device, ungrab_window);`

$ * + !

$ * + !

$ * *)! B) $ AnyKey .

$ * * ' ! 8 ') + : * ' ShiftMask , LockMask , ControlMask , Mod1Mask , Mod2Mask , Mod3Mask , Mod4Mask , Mod5Mask .

B) $ AnyModifier , G) +)) G) * $ ' * ' 1) ' * ' * 4!

$ * + ' *) ! ,* A@DD $ *) ' * L + !

$ * ,= * + $ * + !

XUngrabDeviceKey) XUngrabKey *) ! , .$ $ + * . $) + !

XUngrabDeviceKey BadAlloc , BadDevice , BadMatch , BadValue , BadWindow !

Passively Grabbing a Button

8 $ + *) . XGrabDeviceButton . 8 $ * + ') + $ +) $) XOpenDevice *) G) * BadDevice ! ,* $ * +) $$ $) Buttons , G) * BadMatch !

```
int XGrabDeviceButton( *display, *device, button, modifiers, , grab_window, owner_events, event_count, *event_list, this_device_mode, other_device_mode);
```

[illegible]

[illegible]

[illegible] AnyButton .

[illegible] ShiftMask , LockMask , ControlMask , Mod1Mask , Mod2Mask , Mod3Mask , Mod4Mask , [illegible] Mod5Mask .

[illegible] AnyModifier , [illegible]

[illegible]

[illegible]

[illegible] True [illegible] False .

[illegible]

[illegible]

[illegible] GrabModeSync [illegible] GrabModeAsync .

[illegible] GrabModeSync [illegible] GrabModeAsync .

XGrabDeviceButton [illegible] XGrabButton [illegible] XOpenDevice [illegible]

[illegible] XGrabDeviceButton [illegible]

[illegible]

K [illegible]

K [illegible]

K [illegible] XGrabDevice , [illegible] Device- ButtonPress [illegible] DeviceButtonPress [illegible]

[illegible] XGrabDevice . [illegible]

[illegible]

[illegible] AnyModifier [illegible] AnyButton [illegible]

XGrabDeviceButton [illegible] BadAccess [illegible] XGrabDeviceButton [illegible] AnyModifier [illegible] AnyButton , [illegible] BadAccess [illegible]

XGrabDeviceButton [illegible] BadAccess , BadClass , BadDevice , BadMatch , BadValue , [illegible] BadWindow [illegible]

[illegible] XUngrabDeviceButton .

```
int XUngrabDeviceButton( *display, *device, button, modifiers,
*modifier_device, ungrab_window);
```

[illegible]

[illegible]

[illegible] AnyButton .

[illegible] ShiftMask , LockMask , ControlMask , Mod1Mask , Mod2Mask , Mod3Mask , Mod4Mask , [illegible] Mod5Mask .

[illegible] AnyModifier , [illegible]

[illegible]

[illegible]

XUngrabDeviceButton [illegible] XUngrabButton [illegible] XOpenDevice [illegible] BadDevice [illegible]

[illegible] AnyModifier [illegible]

XUngrabDeviceButton [illegible] BadAlloc, BadDevice, BadMatch, BadValue, [illegible] BadWindow [illegible]

Thawing a Device

[illegible] XAllowDeviceEvents.

```
int   XAllowDeviceEvents( *display,   *device,   event_mode,   time);
```

[illegible]

[illegible]

[illegible] AsyncThisDevice, SyncThisDevice, AsyncOtherDevices, ReplayThisDevice, AsyncAll, [illegible] SyncAll.

[illegible] CurrentTime.

XAllowDeviceEvents [illegible]

- AsyncThisDevice
- [illegible] AsyncThisDevice [illegible] AsyncThisDevice [illegible]
- SyncThisDevice
- [illegible] SyncThisDevice [illegible]
- ReplayThisDevice

- [illegible] GrabDeviceButton [illegible] AllowDeviceEvents [illegible] SyncThisDevice , [illegible] Grab), [illegible]

- AsyncOtherDevices

- [illegible] AsyncOtherDevices [illegible] AsyncOtherDevices [illegible]

- SyncAll

- [illegible] SyncAll [illegible] SyncAll [illegible] SyncAll [illegible]

- AsyncAll

- [illegible] AsyncAll [illegible] AsyncAll [illegible] AsyncAll [illegible]

AsyncThisDevice , [illegible] SyncThisDevice , [illegible] ReplayThisDevice [illegible] AsyncOtherDevices [illegible] SyncAll [illegible] AsyncAll , [illegible]

[illegible]

XAllowDeviceEvents [illegible] BadDevice [illegible] BadValue [illegible]

Controlling Device Focus

[illegible] XGetDeviceFocus [illegible] XSetDeviceFocus [illegible]

XSetInputFocus□*)□□□□□□□□□.□□$□□□□□□□□□□□□+□□□□,=□□□□$□□□□□□□□□□□□*)□□□□□□□$□□□'□□□□! :□□□□□□□□□□□□□□□□□□*□□)□□□□□□FollowKeyboard ,□□□□$□□+□□□□□*□□□□.□□□□□□□□□□□+□□□□!

8□□□□□□□□□□□□)□□□□□□□*□□)□□□□□□□□□□□□□+□□□□□□□□□□□□□□□□*□□)□□□□'□□□*□□□□□.□□□□□□□□□□□+□□□□)□□□XGetDeviceFocus .

int **XGetDeviceFocus**(**display*, **device*, **focus_return*, **revert_to_return*, **focus_time_return*);

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□!

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□+□□□!

□$□□□*□□□□ □□□□ □□□□□□□□□ □*□ □□ +□□□□□□□□ □□□□□ □□□□□□ □□□ □□□+□□□ □□□□ □□□)□□□ □□□□,=□ □*□ □□□□ □□□□□□□□ □□□□□ □□□□ □□□□□□□□□□□□+□□□□*□□)□□□□□□□□□□□*□□□□□□□□None,□□□ PointerRoot ,□□□FollowKeyboard .

□$□□□*□□□□ □□□□ □□□□□□□□□ □*□ □□ +□□□□□□□□ □□□□□ □□□□□□ □□□ □□□+□□□□□□□□□□□)□□□□□□□□)□□□□□□□□+□□□L□□□□□□□)□□*□□□□□ □□+□□□!

□$□□□*□□□□ □□□□ □□□□□□□□□ □*□ □□ +□□□□□□□□ □□□□□ □□□□□□ □□□ □□□+□□□□□□□□□□□)□□□□□□□*□□)□□□□'□□□□□□□□□□□□*□□□□□□□□□□□ +□□□!

XGetDeviceFocus□ □□□)□□□□ □□□□*□□)□□ □□□□□□□□ □□□□ □□+□□□□□□□□ □□□□□□□□ □□□□ □□□□ □□□□□*□□ □)□□□□'□□*□□□□□□□.□□□□□□□□□□□$)□□□□+□□□!

XGetDeviceFocus□□□□□□□□□□□□□□BadDevice□□□□□BadMatch□□□□□□□!

8□□□□□□□□□□□*□□)□□□*□□□□□.□□□□□□□□□□□+□□XSetDeviceFocus .

int **XSetDeviceFocus**(**display*, **device*, *focus*, *revert_to*, *time*);

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□!

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□+□□□!

□$□□□*□□□□□□□□,=□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□□I□□*□□ □)□□□□□)□□□□□□□□□!□8□□□□'□□□□□□□□□□□□□□□□,=□Point-erRoot ,□FollowKeyboard ,□□□None .

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□*□□)□□□*□□□□□□+□□□□□□)□□ □□+□□□□□*□□□□*□□)□□□□□□□□□□□□□'□□□□□□+□□□□□□□!□:□□ □*□□□□□*□□□□□□□□□□□□□□□□□□□□'□□□□□$□□□7□RevertToPar-ent ,□RevertToPointerRoot ,□RevertToNone ,□□□Re-vertToFollowKeyboard .

□$□□□*□□□□□□□□□□□'□!□B□)□□□□□$□□□□□□□□□□□□□□□□□□'□□□□'$□□□.□ $□□□□□□□□□□□'□□□□□□□□□□□□□□□□□CurrentTime .

XSetDeviceFocus□□□□□□□□□□□□*□□)□□*□□□□□□.□□□□□□□□□□$)□□□□+□□□□□□□□□□□□□□□□□□ *□□)□□□□□□□□□□□□'□!□,□□□□□□□□□□□**□□□□□*□□□□□□$□□□*□□□□□□'□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□*□□ □)□□□□□□□□□□□□□'□□□□□□□□□□□□□□□□□□□□□□□□□□)□□□□□□□□□□□□+□□□□□'□!□:□□□□□□□□□□□□□□□□□□□□□□□□□*□□ □)□□□□□□□□□□□□□'□□□□□□□□□□□□□□□□□□□□□$□□□*□□□□□□'□!□8□□□□*)□□□□□□□□□□□)□□□□□□□□□□□□□□□+□□□□□ □□□□□□□□DeviceFocusIn□□□□□DeviceFocusOut□□+□□□□!

[illegible]

- [illegible] None , [illegible]

- [illegible]

- [illegible] PointerRoot , [illegible]

- [illegible] FollowKeyboard , [illegible]

[illegible] XSetDeviceFocus [illegible] BadMatch [illegible]

- [illegible] RevertToParent , [illegible] RevertToNone .

- [illegible] RevertToPointerRoot , RevertToFollowKeyboard , [illegible] RevertToNone , [illegible]

[illegible] DeviceFocusIn [illegible] DeviceFocusOut [illegible]

XSetDeviceFocus [illegible] BadDevice , BadMatch , BadValue , [illegible] BadWindow [illegible]

Controlling Device Feedback

[illegible] XGetFeedbackControl .

XFeedbackState * **XGetFeedbackControl**(*display*, *device*, *num_feedbacks_return*);

[illegible]

[illegible]

[illegible]

XGetFeedbackControl [illegible] FeedbackState [illegible] XFeedbackState [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
} XFeedbackState;
```

[illegible]

- [illegible] <X11/extensions/XI.h>. [illegible] KbdFeedbackClass, PtrFeedbackClass, StringFeedbackClass, IntegerFeedbackClass, LedFeedbackClass, [illegible] BellFeedbackClass.
- [illegible] FeedbackState [illegible]
- [illegible]

[illegible] KbdFeedback [illegible] XKbdFeedbackState [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int click;
     int percent;
     int pitch;
     int duration;
     int led_mask;
     int global_auto_repeat;
     char auto_repeats[32];
} XKbdFeedbackState;
```

[illegible] XKbdFeedbackState [illegible]

- [illegible]
- [illegible]
- [illegible]

K 8□□□□)□□□□□□□'□'□□□□□$□□□*□□□□□□□□□)□□□□□□□□□'□□□□□□□□□□□□*□□□□□□□□!

K 8□□□□□□L'□□□□'□'□□□□□□□□□□□□□'□□□□□□□□□□□□□□□□□□□□□□□)□□□□□□□□□□□□*□)$□□□□J0 D9=□!□(□+□□)□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□$□□□□□□□D9=□□□□□□!

K 8□□□□□□□□□L□)□□L□□$□□□□'□'□□□□□□□□□+□□)□□*□ `AutoRepeatModeOn` □□□ `AutoRepeat-ModeOff` .

K 8□□□□)□□L□□$□□□□□'□'□□□□□□□□□□□□□□+□□□□□!□9□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□)□□□□□□ $□□□□□□□□□□□□□□□*□□□□□□□□□□□□□$□□□□□□□□□□!□8□□□+□□□□□□□□□□□$□□□□□□□□□□□□□J0□□□□□□! E□□□□A□1*□□'□"4□□□□□□□□□□□□□□□□□□□□*□□□□□□□□&A□□□□&A□N□ □□□□□□□□□□□□□□□□□□□□□□□□*□□□□□ □□□□□□□□□□□□□□□□□□□$□□□□□□□□□□□□□□□&A!

8□□□□□*□□□□□□□□□□□□G)□+□□□□□□□□□□□□□□□□□□□)$$□□□□□□□□□□□□□□□□□□□□$□□□□□□□□□□□□$□□□□□ □□□□□□□ `PtrFeedback` □)□□□□□□□□ `XPtrFeedbackState` □□□□)□□)□□□□□□□□□□□□□□□□*□□□□□□□ *□□□□□7

```
typedef struct {
     XID class;
     int length;
     XID id;
     int accelNum;
     int accelDenom;
     int threshold;
} XPtrFeedbackState;
```

8□□□□□□□□□□□□□□'□'□□□□□□*□□□ `XPtrFeedbackState` □□□□)□□)□□□□□$□□□□□□□□□)□□□□□ □□□□□□□*□□□□□*□□□□□□□7

K 8□□□□□□□□A)'□'□'□□□□□□□□)□□□□□□□□□□)'□□□□□□□□*□□□□□□□□□□□□□□□□□□□□□□□')□□□□$□□□□!

K 8□□□□□□□□=□□□'□'□'□□□□□□□)□□□□□□□□□□□□□□'□□□□□□□□*□□□□□□□□□□□□□□□□□□□□□□□')□□□□$□□□□!

K 8□□□□□□□□=□□□'□'□'□□□□□□□)□□□□□□□□□□□□□□□□□□□□*□□□□□□□□□□□□□□□□□□□□□□□□!

,□□□□□□*□□□□□□□□□□□□□□□□□□□□□□□$□□□□□□*□□□□$□□□□□□□□□□□□□□□□□)'□□□□□□□□□□□$□□□□□ +□□□□ `XIntegerFeedbackState` □□□□)□□)□□!□8□□□'□□□')'□□□□□'□.□')'□+□□)□□□□□□□ □□□□□□□□□□□□$□□□□□□□□□□□$□□□□□!

```
typedef struct {
     XID class;
     int length;
     XID id;
     int resolution;
     int minVal;
     int maxVal;
} XIntegerFeedbackState;
```

8□□□□□□□□□□□□□□'□'□□□□□□*□□□ `XIntegerFeedbackState` □□□□)□□)□□□□□$□□□□□□□□□□□□$□□ □□□□□□□□□□*□□□□□*□□□□□□□7

- [illegible]

- [illegible]

- [illegible]

[illegible] `XStringFeedbackState` [illegible] `KeySyms` [illegible] `XGetFeedbackControl` [illegible] `XStringFeedbackState` [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int max_symbols;
     int  num_syms_supported;
     KeySym *syms_supported;
} XStringFeedbackState;
```

[illegible] `XStringFeedbackState` [illegible]

- [illegible]

- [illegible]

- [illegible]

[illegible] `XBellFeedbackState` [illegible] `KbdFeedback` [illegible] `BellFeedback` [illegible] `KbdFeedbackState` [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int percent;
     int pitch;
     int duration;
} XBellFeedbackState;
```

[illegible] XLed [illegible] FeedbackState [illegible] KbdFeedback [illegible] LedFeedback [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     Mask led_values;
     Mask led_mask;
} XLedFeedbackState;
```

XGetFeedbackControl [illegible] BadDevice [illegible] BadMatch [illegible]

[illegible] XGetFeedbackControl [illegible] XFreeFeedbackList .

void **XFreeFeedbackList**(**list*);

[illegible] XFeedbackState [illegible] XGetFeedbackControl .

XFreeFeedbackList [illegible]

[illegible] XChangeFeedback-Control . [illegible] XFeedbackControl [illegible]

int **XChangeFeedbackControl**(**display*, **device*, *valuemask*, **value*);

[illegible]

[illegible]

[illegible]

[illegible] XFeedbackControl [illegible]

XChangeFeedbackControl [illegible] XFeedbackControl [illegible] XFeedbackControl [illegible]

```
typedef struct {
```

```
     XID class;
     int length;
     XID id;
} XFeedbackControl;
```

[illegible] KbdFeedback [illegible] KbdFeedbackControl [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int click;
     int percent;
     int pitch;
     int duration;
     int led_mask;
     int led_value;
     int key;
     int auto_repeat_mode;
} XKbdFeedbackControl;
```

[illegible] XKbdFeedbackControl [illegible] AutoRepeatModeOn , [illegible] AutoRepeatModeOff , [illegible] AutoRepeatModeDefault .

[illegible]

```
#define   DvKeyClickPercent          (1><<0)
#define   DvPercent                  (1><<0)
#define   DvPitch                    (1><<0)
#define   DvDuration                 (1><<0)
#define   DvLed                      (1><<0)
#define   DvLedMode                  (1><<0)
#define   DvKey                      (1><<0)
#define   DvAutoRepeatMode           (1><<0)
```

[illegible] PtrFeedback [illegible] PtrFeedbackControl [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int accelNum;
```

```
    int accelDenom;
    int threshold;
} XPtrFeedbackControl;
```

[illegible]

[illegible]

```
#define    DvAccelnum        (1L<<0)
#define    DvAccelDenom      (1L<<1)
#define    DvThreshold       (1L<<2)
```

[illegible] `BadValue` [illegible]

[illegible] `BadMatch` [illegible] `Relative` [illegible] `Absolute` [illegible] `XSetDeviceMode` [illegible]

[illegible] `IntegerFeedback` [illegible] `IntegerFeedbackControl` [illegible]

```
typedef struct {
    XID class;
    int length;
    XID id;
    int int_to_display;
} XIntegerFeedbackControl;
```

[illegible]

```
#define   DvInteger          (1L<<0)
```

[illegible] `StringFeedback` [illegible] `StringFeedbackControl` [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int num_keysyms;
     KeySym *syms_to_display;
} XStringFeedbackControl;
```

[illegible]

```
#define   DvString           (1L<<0)
```

[illegible] `BellFeedback` [illegible] `BellFeedbackControl` [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int percent;
     int pitch;
     int duration;
} XBellFeedbackControl;
```

[illegible]

```
#define   DvPercent                  (1L<<1)
#define   DvPitch                    (1L<<2)
#define   DvDuration                 (1L<<3)
```

[illegible] `LedFeedback` [illegible] `LedFeedbackControl` [illegible]

```
typedef struct {
     XID class;
     int length;
     XID id;
     int led_mask;
     int led_values;
} XLedFeedbackControl;
```

[illegible]

```
#define   DvLed                      (1L<<4)
```

```
#define   DvLedMode                   (1L<<5)
```

XChangeFeedbackControl□□□□□□□□□□□□□□BadDevice ,□BadFeedBack ,□BadMatch , □□□□BadValue□□□□□□□□!

Ringing a Bell on an Input Device

8□□□□□□□□□□□□□□□□□□□□□□□□.□□□□□□□□□□□$)□□□□+□□□□□)□□□XDeviceBell .

int **XDeviceBell**(**display*, **device*, *feedbackid*, *percent*);

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□!

□$□□□*□□□□□□□□□□□□□□□□□□□□□+□□□!

□$□□□*□□□□ □□□□ *□□□□□□□□□□□□□!□ □□□□□□ +□□)□□□KbdFeedbackClass□□□□BellFeedbackClass .

□$□□□*□□□□□□□□□,=□□*□□□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□!

□$□□□*□□□□□□□□+□□)'□□□□□□□□□□□□□□□□□□□□""□1G)□□□4□□□□□""$□□□□□□□1□□)□4!

XDeviceBell□□□□□□□□□□□□)□□□□□□□□□□□XBell□□*)□□□□□□!□,□□□□□□□□□□□□□□$□□□*□□□□□□□□□□□□□□□□$□□□*□□□□□$)□□□□+□□□□*□□□□□□□□□)□□□□□□□□□□□$□□□*□□□□+□□)'□!□8□□□□$□□□*□□□+□□)'□□□□□□□□□□□+□□□□□□□□□□□□□□□+□□)'□□*□□□□□□□*□□□□□□□!□,*□□□□□+□□)□□*□□□□□□□□$□□□□□□□□)'□□□□□□□□□□□□□□□□□□□□□□□□□□□""□□□□□""□□□□□)□□BadValue□□□□□□□□□□□)□□□!□8□□+□□)'□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□$□□□□□□□□□)'□□□□□□□□□□□□□□□□+□□□□7

```
base – [(base * percent) / 100] + percent
```

8□□□+□□)'□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□$□□□□□□□□□)'□□□□□□□□□□□□□+□□□□7

```
base + [(base * percent) / 100]
```

8□□□□□□□□□□□□□□□□□+□□)'□□□*□□□□□□□□□□XChangeFeedbackControl .

XDeviceBell□□□□□□□□□□□□□□BadDevice□□□□BadValue□□□□□□□□!

Controlling Device Encoding

8□□□□□□□□□□□□□□'□$$□□□□□*□□□□□.□□□□□□□□□□+□□□□□□□□□□)$$□□□□□□□$)□□□□)□□Keys ,□□□□XGetDeviceKeyMapping .

KeySym * **XGetDeviceKeyMapping**(**display*, **device*, *first_keycode_wanted*, *keycode_count*, **keysyms_per_keycode_return*);

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□!

□$□□□*□□□□□□□□□□□□□□□□□□□□□+□□□!

□$□□□*□□□□□□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□)□□□□!

□$□□□*□□□□□□□□□)'□□□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□)□□□□!

)('*'$!

XGetDeviceKeyMapping)XGetKeyboardMapping*)!,
)'*$*)'*$*.
+!

XGetDeviceKeyMapping)'*$*)'*
$*.+$!8
*LL')G)')
XListInputDevicesG)1BadValue)4!8*
+)7

```
first_keycode_wanted + keycode_count - 1
```

')G)'.)XListInputDevices
G)1BadValue)4!

8)'**'*7

```
keycode_count * keysyms_per_keycode_return
```

(C9BB)'A1)*'F4*C.1)
*'F4'**7

```
(K - first_keycode_wanted) * keysyms_per_keycode_return + N
```

8'L$LL)+)+
)$G)'!(C9BBNoSymbol*
)*)))'*+)!

8*)*)XFree)!

,*$*+*$XOpenDevice+,
G)*BadDevice!,*+)$$$)
Keys ,G)*BadMatch!

XGetDeviceKeyMapping BadDevice , BadMatch , BadValue
!

8'$$*.+)$$$)
Keys ,)XChangeDeviceKeyMapping .

int **XChangeDeviceKeyMapping**(**display*, **device*, *first_keycode*, *keysyms_per_keycode*, **keysyms*, *num_codes*);

$*+!

$*+!

$**!

$*')!

$*$*'!

□$□□□*□□□□□ □□□□□ □)'□□□□□ □*□ □□□□□□□□□□□□ □□□□□□ □□□□□ □□□□ □□ □□□□□□□□□!

XChangeDeviceKeyMapping□ □□□□ □□□□□□□□□)□□ □□□□ □□□□□ □XChangeKeyboardMapping *)□□□□□□□!□,□□□□□*□□□□□□□□□□□□□□'□□□□□□*□□□□□□□□□$□□□□*□□□□□□)'□□□□□□*□□□□□□□□□□□□*□□□□□□□□□□□$□□□□ □*□□□□□□.□□□□□□□□□□□□□□□□□□□□□□□+□□□□!

,*□□□□□□□$□□□□*□□□□□□□+□□□□□□□□□□□□□□*□□□□□□□□□□□□$□□□□□□□□□□□□□□□XOpenDevice+□□□, □□□□□□□□G)□□□□□□□□□□□*□□□□□BadDevice□□□□□□!□,*□□□□□□□$□□□□*□□□□□□□+□□□□□□□□□□□□□□□□□)$$□□□□ □□$)□□□□□□□Keys ,□□□□□□□□G)□□□□□□□□□□□*□□□□□BadMatch□□□□□□□!

8□□□□ □)'□□□□□ □*□ □□□□'□□□□□□ □□□□ □□□□□ □□□□□□'□□ □□□□□□ ')□□□□ □□□□ □□ ')□□□□$□□□□ □* □□□□□□'□L$□□L□□□□□□□□!□ :□□□□□□□□□□□□□ XChangeDeviceKeyMapping□ □□□□□□□□□□□□ □ BadLength□□□□□□!□8□□□□□$□□□□*□□□□□*□□□□□L□□□□□□□□□')□□□□□□□□□□□□□□□□□□□□□□□□□□□□□G)□□□□□□□□□□ '□□L□□□□□□□□□+□□)□□□□□□)□□□□□□□□□□□□□ListInputDevices□□□G)□□□□□□□□□□□□□□□□□□G)□□□□□□□□□ *□□□□□□□□□□□BadValue□□□□□□!□,□□□□□□□□□□□□□□□□*□□□□□□*□□□□□□□□□□□□.$□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ □□□□□'□.L□□□□□□□□□+□□)□□□□□)□□□□□□□□□□□□ListInputDevices□□□G)□□□□□□□□□□□□G)□□□□□□□□ *□□□□□□□□□□□BadValue□□□□□□7

```
first_keycode + (num_codes / keysyms_per_keycode) - 1
```

XChangeDeviceKeyMapping□□□□□□□□□□□□□□□□BadAlloc ,□BadDevice ,□BadMatch , □□□□BadValue□□□□□□□!

8□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□)□□□□□□□'□□□*□□□□□□□□□□□□□□.□□□□□□□□□□□+□□□□□□□□□□□)$□ $□□□□□□□□$)□□□□□□Keys ,□)□□□XGetDeviceModifierMapping .

```
XModifierKeymap *  XGetDeviceModifierMapping( *display,  *device);
```

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□!

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□+□□□!

XGetDeviceModifierMapping□□□□□□□□□□□)□□□□□□□□□□XGetModifierMapping□*)□□□ □□□□!□8□□□XGetDeviceModifierMapping□*)□□□□□□□□□□□)□□□□□□□□□□□□□□□□□□□□XModifierKeymap□□□□)□□)□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□)□□□□□□□'□□□*□□□□□*□□□□□□□□□$□□□□ *□□□□□□+□□□!□8□□□□□□)□□)□□□□□□)□□□□□□*□□□□□□*□□□□)XFreeModifierMapping . ,*□□□□□□F□□□□+□□)□□□□$$□□□□□□□□□□□□□□□□□□□*□□□□□□□'□□□*□□□□□□□□□□□'□□□*□□□□□□□□□□□□□□□□□!

XGetDeviceModifierMapping□□□□□□□□□□□□□□□BadDevice□□□□BadMatch□□□□□□□!

8□□ □□□□□ □□□□□□□ □□□□□□□□□□□ □□□□□ □□□□ □□□□)□□□□□ □□□□'□□□*□□□□□*□□□□ □□□ □.□□□□□□□□□ □□+□□□□□)□□ XSetDeviceModifierMapping .

```
int  XSetDeviceModifierMapping( *display,  *device,  *modmap);
```

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□!

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□+□□□!

□$□□□*□□□□□□$□□□□□□□□□□□□XModifierKeymap□□□□)□□)□□!

XSetDeviceModifierMapping□□□□□□□□□□□)□□□□□□□□□□XSetModifierMapping□*)□□□ □□□□!□8□□XSetDeviceModifierMapping□*)□□□□□□□□□$□□□□*□□□□□□□□□□□□□□□□□□□□□□□*□□□□□□□□□□□ □*□ □□□□□□ □□□□□□ □□□□□ □□□□ □□□□)□□□□□ □□□□'□□□*□□□□!□(□F□□□□+□□)□□'□□□□□□ □□□□□□ □□□ □□□□□ □□□□)□□ □□□)□□□!□A□□□□□□□□□)'□□□□□□□□□□□□+□□□□□□□□□'□□□□□F□□□□□□□□□□□□□□+□□)□!□:□□□□□□□□□□□

XSetDeviceModifierMapping [illegible] BadValue [illegible] XModifierKeymap [illegible] Shift, Lock, Control, Mod1, Mod2, Mod3, Mod4, [illegible] Mod5. [illegible] XListInputDevices [illegible] XSetModifierMapping [illegible] BadValue [illegible] BadValue [illegible]

[illegible] MappingFailed, [illegible] MappingBusy, [illegible] XSetModifierMapping [illegible] DeviceMappingNotify [illegible] MappingSuccess [illegible]

XSetDeviceModifierMapping [illegible] BadAlloc, BadDevice, BadMatch, [illegible] BadValue [illegible]

Controlling Button Mapping

[illegible] XSetDeviceButtonMapping.

```
int  XSetDeviceButtonMapping( *display,  *device,  map[],  nmap);
```

[illegible]

[illegible]

[illegible]

[illegible]

XSetDeviceButtonMapping [illegible] DeviceMappingNotify [illegible] XSetDeviceButtonMapping [illegible] MappingSuccess. [illegible] XGetDeviceButtonMapping [illegible] BadValue [illegible] BadValue [illegible] XSetDeviceButtonMapping [illegible] MappingBusy, [illegible]

XSetDeviceButtonMapping [illegible] BadDevice, BadMatch, [illegible] BadValue [illegible]

[illegible] XGetDeviceButtonMapping.

```
int  XGetDeviceButtonMapping( *display,  *device,  map_return[],  nmap);
```

[illegible]

[illegible]

[illegible]

[illegible]

XGetDeviceButtonMapping [illegible] XGetDeviceButtonMapping [illegible]

XGetDeviceButtonMapping [illegible] BadDevice [illegible] BadMatch [illegible]

Obtaining the State of a Device

[illegible] XQueryDeviceState .

```
XDeviceState *  XQueryDeviceState( *display,  *device);
```

[illegible]

[illegible]

XQueryDeviceState [illegible] XDeviceState [illegible]

```
typedef struct {
     XID device_id;
     int num_classes;
     XInputClass *data;
} XDeviceState;
```

[illegible]

```
typedef struct {
     unsigned char class;
     unsigned char length;
} XInputClass;
```

[illegible] X11/extensions/XI.h [illegible] KeyClass , ButtonClass , [illegible] ValuatorClass .

[illegible]

[illegible] XValuatorState [illegible]

```
     DeviceMode      1 << 0      Relative = 0, Absolute = 1
     ProximityState      1 << 1      InProximity = 0, OutOfProximity = 1
```

[illegible] Relative , [illegible]

```
typedef struct {
     unsigned char class;
     unsigned char length;
     unsigned char num_valuators;
     unsigned char mode;
     int *valuators;
} XValuatorState;
```

[illegible] XKeyState [illegible]

```
typedef struct {
     unsigned char class;
     unsigned char length;
     short num_keys;
     char keys[32];
} XKeyState;
```

[illegible] XButtonState [illegible]

```
typedef struct {
     unsigned char class;
     unsigned char length;
     short num_buttons;
     char buttons[32];
} XButtonState;
```

XQueryDeviceState [illegible] BadDevice [illegible]

[illegible] XFreeDeviceState .

```
void  XFreeDeviceState( *state);
```

[illegible] XDeviceState [illegible] XQueryDeviceState .

XFreeDeviceState [illegible]

Events

[illegible]

K [illegible]

K [illegible]

K [illegible]

Event Types

[illegible]

[illegible] < X11/ [illegible] X.h > [illegible]

[illegible] XOpenDevice [illegible]

[illegible]

[illegible]

[illegible]	[illegible]
[illegible]	DeviceKeyPress
V	DeviceKeyRelease
[illegible]	DeviceButtonPress
V	DeviceButtonRelease
V	DeviceMotionNotify
[illegible]	DeviceFocusIn
V	DeviceFocusOut
[illegible]	DeviceStateNotify

[illegible]	[illegible]
[illegible]	ProximityIn
V	ProximityOut
[illegible]	DeviceMappingNotify
[illegible]	ChangeDeviceNotify

Event Classes

[illegible]

[illegible] <X11/ [illegible] X.h >. [illegible]

[illegible] XOpenDevice [illegible] XSelectExtensionEvent [illegible]

[illegible] DeviceButtonPress [illegible] DeviceButtonRelease [illegible] DeviceButtonPress [illegible] DeviceButtonPressGrab [illegible] DeviceButtonPress [illegible] DeviceButtonPress [illegible]

[illegible] DeviceButtonPressGrab [illegible] DeviceButtonPress [illegible] DeviceButtonPressGrab [illegible] Access [illegible]

[illegible] DeviceButtonPress [illegible]

[illegible] DeviceMotion [illegible] DeviceButton1Motion [illegible] DeviceButton5Motion . [illegible]

Event Structures

[illegible] <X11/extensions/XInput.h >. [illegible]

[illegible]	[illegible] DeviceKeyPress [illegible] XDeviceKeyPressEvent [illegible]

[illegible]	[illegible]
[illegible]	[illegible] `True` [illegible] `XSendEvent` [illegible]
[illegible]	[illegible]

[illegible]

Device Key Events

[illegible] `Valuators` [illegible]

[illegible]

[illegible] `XDeviceKeyEvent` [illegible]

```
typedef struct {
     int type;                      /* of event */
     unsigned long serial;          /* # of last request processed */
     Bool send_event;               /* true if from SendEvent request */
     Display *display;              /* Display the event was read from */
     Window window;                 /* "event" window reported relative to */
     XID deviceid;
     Window root;                   /* root window event occurred on */
     Window subwindow;              /* child window */
     Time time;                     /* milliseconds */
     int x, y;                      /* x, y coordinates in event window */
     int x_root;                    /* coordinates relative to root */
     int y_root;                    /* coordinates relative to root */
     unsigned int state;            /* key or button mask */
     unsigned int keycode;          /* detail */
     Bool same_screen;              /* same screen flag */
     unsigned int device_state;     /* device key or button mask */
     unsigned char axes_count;
     unsigned char first_axis;
     int axis_data[6];
```

```
} XDeviceKeyEvent;

typedef XDeviceKeyEvent XDeviceKeyPressedEvent;
typedef XDeviceKeyEvent XDeviceKeyReleasedEvent;
```

Device Button Events

[illegible] `Valuators ,` [illegible]

[illegible]

```
typedef struct {
     int type;                        /* of event */
     unsigned long serial;            /* # of last request processed by server */
     Bool send_event;                 /* true if from a SendEvent request */
     Display *display;                /* Display the event was read from */
     Window window;                   /* "event" window reported relative to */
     XID deviceid;
     Window root;                     /* root window that the event occurred on */
     Window subwindow;                /* child window */
     Time time;                       /* milliseconds */
     int x, y;                        /* x, y coordinates in event window */
     int x_root;                      /* coordinates relative to root */
     int y_root;                      /* coordinates relative to root */
     unsigned int state;              /* key or button mask */
     unsigned int button;             /* detail */
     Bool same_screen;                /* same screen flag */
     unsigned int device_state;       /* device key or button mask */
     unsigned char axes_count;
     unsigned char first_axis;
     int axis_data[6];
} XDeviceButtonEvent;

typedef XDeviceButtonEvent XDeviceButtonPressedEvent;
typedef XDeviceButtonEvent XDeviceButtonReleasedEvent;
```

Device Motion Events

[illegible]

[illegible]

[illegible]

```
typedef struct {
     int type;                          /* of event */
     unsigned long serial;              /* # of last request processed by server */
     Bool send_event;                   /* true if from a SendEvent request */
     Display *display;                  /* Display the event was read from */
     Window window;                     /* "event" window reported relative to */
     XID deviceid;
     Window root;                       /* root window that the event occurred on */
     Window subwindow;                  /* child window */
     Time time;                         /* milliseconds */
     int x, y;                          /* x, y coordinates in event window */
     int x_root;                        /* coordinates relative to root */
     int y_root;                        /* coordinates relative to root */
     unsigned int state;                /* key or button mask */
     char is_hint;                      /* detail */
     Bool same_screen;                  /* same screen flag */
     unsigned int device_state;         /* device key or button mask */
     unsigned char axes_count;
     unsigned char first_axis;
     int axis_data[6];
} XDeviceMotionEvent;
```

Device Focus Events

[illegible]

`DeviceFocusIn` [illegible] `DeviceFocusOut` [illegible]

```
typedef struct {
     int type;                      /* of event */
     unsigned long serial;          /* # of last request processed by server */
     Bool send_event;               /* true if this came from a SendEvent request */
     Display *display;              /* Display the event was read from */
     Window window;                 /* "event" window it is reported relative to */
     XID deviceid;
     int mode;                      /* NotifyNormal, NotifyGrab, NotifyUngrab */
     int detail;
```

```
                                        /*
                                         * NotifyAncestor, NotifyVirtual, NotifyInferior,
                                         * NotifyNonLinear,NotifyNonLinearVirtual, NotifyPointer
                                         * NotifyPointerRoot, NotifyDetailNone
                                         */
     Time time;
} XDeviceFocusChangeEvent;

typedef XDeviceFocusChangeEvent XDeviceFocusInEvent;
typedef XDeviceFocusChangeEvent XDeviceFocusOutEvent;
```

Device StateNotify Event

8□□□□□+□□□□□□□□□□□□□□□)□□□□□□□□□□□□□□□□□□□'□$□□+□□□□□)□□□□$□□□□□□□□□□□□)□□□□□□□□□□□□□□□□* □□□□□□+□□□□*□□□□□□□□□□□□$)□□□□□□□□□□□□□□□□□□□□□)$$□□□□!□,□□□□□□□□□□□□□□□□□□Device-□□+□□□□ FocusIn□□+□□□□□□EnterNotify□□+□□□□□□□□□□□□□□□□□+□□□□□□□□□□□□□□□□□□□□□□□□□+□□□□□□□□□□□ XDeviceStateNotify□□+□□□□!

,*□□□□□□□□+□□□□□□)$$□□□□□□□□$)□□□Valuators ,□□□□□□'□□□□'□'□□□□□□□□□□□□□□XValuatorStatus□□□□)□□)□□□□□□□□□□□□□'□□□□□□□□□□□□□□$□□□□□□□□□□□□□+□□□□'□□□□□□$□□.□'□□□□□□□□□□□□□□□□□ □□□□□□□□□□□□□□□□□□*□□'□□□□□!□8□□□*□□□□□□□□□□□□□□□□□□□□□□□□)□□□□□□□□□□□□□*□□□□7

```
     0x01     Relative = 0, Absolute = 1
     0x02     InProximity = 0, OutOfProximity = 1
```

,*□□□□□□□□+□□□□□□)$$□□□□□□'□□□□+□□)□□□□□□□□□□□□□□□□□□□□□□□□□□$□□□□□□□□□□□XEvent□□□□,□□□ ')□□□□$□□□XDeviceStateNotify□□+□□□□□□□□□□□□□□□□□□□□□□□□□□□□□!

```
typedef struct {
     unsigned char class;
     unsigned char length;
} XInputClass;

typedef struct {
     int type;
     unsigned long serial;     /* # of last request processed by server */
     Bool send_event;          /* true if this came from a SendEvent request */
     Display *display;         /* Display the event was read from */
     Window window;
     XID deviceid;
     Time time;
     int num_classes;
     char data[64];
} XDeviceStateNotifyEvent;

typedef struct {
     unsigned char class;
     unsigned char length;
     unsigned char num_valuators;
```

```
     unsigned char mode;
     int valuators[6];
} XValuatorStatus;

typedef struct {
     unsigned char class;
     unsigned char length;
     short num_keys;
     char keys[32];
} XKeyStatus;

typedef struct {
     unsigned char class;
     unsigned char length;
     short num_buttons;
     char buttons[32];
} XButtonStatus;
```

Device Mapping Event

[illegible] `MappingNotify` [illegible]

```
typedef struct {
     int type;
     unsigned long serial;
     Bool send_event;
     Display *display;
     Window window;
     XID deviceid;
     Time time;
     int request;
     int first_keycode;
     int count;
} XDeviceMappingEvent;
```

ChangeDeviceNotify Event

[illegible]

```
typedef struct {
     int type;
     unsigned long serial;
     Bool send_event;
     Display *display;
     Window window;
     XID deviceid;
```

```
     Time time;
     int request;
} XChangeDeviceNotifyEvent;
```

Proximity Events

[illegible]

[illegible] Valuators [illegible]

```
typedef struct {
     int type;                  /* ProximityIn or ProximityOut */
     unsigned long serial;      /* # of last request processed by server */
     Bool send_event;           /* true if this came from a SendEvent request */
     Display *display;          /* Display the event was read from */
     Window window;
     XID deviceid;
     Window root;
     Window subwindow;
     Time time;
     int x, y;
     int x_root, y_root;
     unsigned int state;
     Bool same_screen;
     unsigned int device_state;    /* device key or button mask */
     unsigned char axes_count;
     unsigned char first_axis;
     int axis_data[6];
} XProximityNotifyEvent;

typedef XProximityNotifyEvent XProximityInEvent;
typedef XProximityNotifyEvent XProximityOutEvent;
```

Event Handling Functions

[illegible]

- [illegible]
- [illegible]
- [illegible]

- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]

Determining the Extension Version

```
XExtensionVersion *  XGetExtensionVersion( *display,  *name);
```

[illegible]

[illegible]

XGetExtensionVersion [illegible]

[illegible] XExtensionVersion [illegible]

```
typedef struct {
     Bool present;
     short major_version;
     short minor_version;
} XExtensionVersion;
```

[illegible] <X11/extensions/XI.h>. [illegible]

[illegible] XFree [illegible]

Listing Available Devices

[illegible] XListInputDevices [illegible] <X11/extensions/XI.h> [illegible] XInternAtom [illegible] XListInputDevices [illegible]

```
XDeviceInfo *  XListInputDevices( *display,  *ndevices);
```

[illegible]

[illegible]

XListInputDevices [illegible] XDeviceInfo [illegible]

[illegible] XDeviceInfo [illegible] IsXPointer [illegible] IsXKeyboard [illegible] IsXExtensionDevice [illegible]

[illegible] XDeviceInfo [illegible]

[illegible] Valuators [illegible] XDeviceInfo [illegible] XValuatorInfo [illegible] XAxisInfo [illegible] XValuatorInfo [illegible] XValuatorInfo [illegible]

[illegible] XDeviceInfo [illegible]

```
typedef struct _XDeviceInfo {
     XID id;
     Atom type;
     char *name;
     int num_classes;
     int use;
     XAnyClassPtr inputclassinfo;
} XDeviceInfo;
```

[illegible] XDeviceInfo [illegible]

```
typedef struct _XKeyInfo {
     XID class;
     int length;
     unsigned short min_keycode;
     unsigned short max_keycode;
     unsigned short num_keys;
```

```
} XKeyInfo;

typedef struct _XButtonInfo {
     XID class;
     int length;
     short num_buttons;
} XButtonInfo;

typedef struct _XValuatorInfo {
     XID class;
     int length;
     unsigned char num_axes;
     unsigned char mode;
     unsigned long motion_buffer;
     XAxisInfoPtr axes;
} XValuatorInfo;
```

8□□□`XAxisInfo`□□□□)□□)□□□$□□□□□□□□□□□□□□`XValuatorInfo`□□□□)□□)□□□□□□□□*□□□□□□ *□□□□□□7

```
typedef struct _XAxisInfo {
     int resolution;
     int min_value;
     int max_value;
} XAxisInfo;
```

8□□□*□□□□□□□□□□□□'□□□'□□□□□□□□□*□□□□□□□`< X11/extensions/XI.h >`□□□□□□□□*□□□!

```
MOUSE      QUADRATURE
TABLET      SPACEBALL
KEYBOARD      DATAGLOVE
TOUCHSCREEN      EYETRACKER
TOUCHPAD      CURSORKEYS
BUTTONBOX      FOOTMOUSE
BARCODE      ID_MODULE
KNOB_BOX      ONE_KNOB
TRACKBALL      NINE_KNOB\s+1
```

8□□□□□□□'□□□□□□□□□□□)□□□□□□□□□`XInternAtom`□□□G)□□□□□□□□□□□)□□□□□□□□□'□□□□□□□□□□□□)□□□□*□□□□□'$□□□□□□□□□□□□□□□□□□□$□□'□'□□□□□*□□`XDeviceInfo`□□□□)□□)□□!

`XListInputDevices`□□□□)□□□□A@DD□□*□□□□□□□□□□□□□□□□□$)□□□□+□□□□□□□□□□□□□!

8□□*□□□□□□□□□□□□□□□□)□□□□□`XListInputDevices` ,□)□□□`XFreeDeviceList` .

```
void  XFreeDeviceList( *list);
```

□$□□□*□□□□□□□□$□□□□□□□□□□□□□□`XDeviceInfo`□□□□□□□□□□)□□□□□□□□□ $□□+□□)□□□□□□□`XListInputDevices` .

XFreeDeviceList [illegible]

Enabling and Disabling Extension Devices

[illegible] XOpenDevice [illegible]

XDevice * **XOpenDevice**(*display*, *device_id*);

[illegible]

[illegible] XListInputDevices [illegible]

XOpenDevice [illegible] XDevice [illegible]

```
typedef struct {
     XID device_id;
     int num_classes;
     XInputClassInfo *classes;
} XDevice;
```

[illegible] XDevice [illegible] XInputClassInfo [illegible]

[illegible] XInputClassInfo [illegible]

```
typedef struct {
     unsigned char input_class;
     unsigned char event_type_base;
} XInputClassInfo;
```

[illegible]

```
     DeviceKeyPress(XDevice *device, event_type, event_class)
```

[illegible] XSelectExtensionEvent [illegible] XNextEvent [illegible]

XOpenDevice [illegible] BadDevice [illegible]

[illegible] XCloseDevice [illegible]

int **XCloseDevice**(**display*, **device*);

[illegible]

[illegible]

XCloseDevice [illegible] XDevice [illegible]

[illegible] XDevice [illegible] XCloseDevice [illegible]

[illegible]

[illegible]

XCloseDevice [illegible] BadDevice [illegible]

Changing the Mode of a Device

[illegible] XSetDeviceMode .

int **XSetDeviceMode**(**display*, **device*, *mode*);

[illegible]

[illegible]

[illegible] Absolute [illegible] Relative .

XSetDeviceMode [illegible] XOpenDevice [illegible] BadDevice [illegible] Valuators [illegible] BadMatch [illegible]

[illegible] DeviceBusy [illegible]

XSetDeviceMode [illegible] BadDevice , BadMatch , BadMode , [illegible] DeviceBusy [illegible]

Initializing Valuators on an Input Device

[illegible]

[illegible] Absolute .

[illegible] XSetDeviceValuators .

```
Status  XSetDeviceValuators( *display,  *device,  num_valuators);
```

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

XSetDeviceValuators [illegible] BadValue [illegible]

```
first_valuator + num_valuators
```

[illegible] Success [illegible] AlreadyGrabbed [illegible]

XSetDeviceValuators [illegible] BadDevice , BadLength , BadMatch , [illegible] BadValue [illegible]

Getting Input Device Controls

[illegible]

[illegible]

[illegible] XGetDeviceControl .

```
XDeviceControl *  XGetDeviceControl( *display,  *device,  control);
```

[illegible]

[illegible]

,□□□□□□*□□□□□□□□□□□$□□□□*□□□□□□+□□□□□□□□□□□□□□□□□□□□□G)□□□□□□!

XGetDeviceControl□□□□)□□□□□□□□□□)□□□□□□□□□□□□□□*□□□□□□□$□□□□*□□□□□□□+□□□□□□□□□□□□□!□,*□□□□ □□□□□□□□□□□□□+□□□□□□□□□□□□□□□)$$□□□□□□□□□□□□□+□□□□□BadValue□□□□□□□□□□□□□□□)□□□□□! ,*□□□□□□□$□□□□*□□□□□□□+□□□□□□□□□□□□□□□□)$$□□□□□□□□□□□+□□□□BadMatch□□□□□□□□□ □□□□)□□□□□!

,*□□□□□□□□G)□□□□□□□□□□)□□□□□□*)□□□□□□$□□□□□□□□□□□□□□□XDeviceState□□□□□)□□)□□□□□□□□□□□ □)□□□□□!□8□□□□□□*□□'□□□□□□□□□□)□□□□□□+□□□□□□□□□□□□□□□□□□□□□□□□□□□$□□□□*□□□□□□□□□□□□□□□□□□□ '□$$□□□□□□□□□□□□□)□□)□□□□□$$□□$□□□□□□□*□□□□□□□□□□□□□□□□□!□8□□□□*□□□□□□□□□□'□'□□□□□□□□□□□□□'□ '□□□□□□□□□□□□□□+□□□□□□□□□□□□□□□□□□□□□□□□□□□*□□□□□□□□□*□□□□□□7

```
typedef struct {
     XID control;
     int length;
} XDeviceState;
\fP
```

8□□□□□□□□□□□□□□'□□□□□□□□□'$□□□□□□□□□□□□□□□□□□□□□□□□□*□□□□□□□□□□□□□□< *X11/exten-sions/XI.h >.□#)□□□□□□□□□□□□□*□□□□□□□□+□□□□□□□□□□□□□□□□□□□□□)□□□=9□,#9L□9□:D@8,:A!

8□□□□□*□□'□□□□□□□□□□)□□□□□□*□□□□□□□=9□,#9L□9□:D@8,:A□□□□□□□□□□□□□□□□*□□□□□□□□□□□□□ XDeviceResolutionState□□□□)□□)□□□□□□□□□□□□□□□□□*□□□□□□□□*□□□□□□7

```
typedef struct {
     XID control;
     int length;
     int num_valuators;
     int *resolutions;
     int *min_resolutions;
     int *max_resolutions;
} XDeviceResolutionState;
```

8□□□□□□+□□□□□□□□□□□□□□□□□□□)□□□□□□□□□□□□□□*□+□□)□□□□□□□□□□□□□□□□□□□□□□□□□*□+□□□□□□□□□□□)□□□□□□□□□□ □□□□□□*□□□□□□□!□□□)□□□□□□□□□□□□□□)'□□□□□□□□□□□□□□□□□□□□□□□□F□□□□1"4!□□□□□□)□□□□□□*□□□□□□ +□□)□□□□□□□□□□□□□□□□+□□□□□□□□□□)□□□□!□;□□□□□□□□+□□)□□□□□□□□□□□□□□□□□+□□□□□□□□□□)□□□□□O□P □□□)□□□□□□□□□)□□□□□□□□□□□□□□□□□*□□□□□□□□□)□□□□□□'□□L□□□□□)□□□□□O□P□□□□)□□□□□□□□'□□□□ ')'□+□□□□□□□□□□□□□□□□□□□□□'□.L□□□□□)□□□□□O□P□□□□)□□□□□□□□□'□.□')'□+□□□□□□□□□□□□□□□!

<□□□□□□□□□□□□□□□□□□□□□□□□$□□□□*□□XGetDeviceControl□*□□□□□□□□□□□BadMatch□□□□□□□□□* □□□□□$□□□□*□□□□□□□+□□□□□□□□□□□□+□□)□□□□□!

XGetDeviceControl□□□□□□□□□□□□□□BadMatch□□□□□BadValue□□□□□□□□!

Changing Input Device Controls

□□'□□□□$)□□□□+□□□□□□)$$□□□□+□□□□)□□□□□*□□)□□□ □□□□□□□!□8□$□□□□□□□□□□□□□□□□)□□□□□□□□□□□□□□□□□□□□□□□F□□□□□□□+□□□□□□□□□□□□□□□□□□□□□□□□□□ □□□*□□)□□□□□□!□8□□□□□□□□*□□)$$□□□□□□□□□□□□□□□□□□□+□□□□*□□'□□□□□□$)□□□□+□□□□□□□□□□

[illegible]

[illegible]

[illegible] `XChangeDeviceControl` .

```
Status  XChangeDeviceControl( *display,  *device,  control,  *value);
```

[illegible]

[illegible]

[illegible]

[illegible] `XDeviceControl` [illegible]

XChangeDeviceControl [illegible] BadValue [illegible] BadMatch [illegible] AlreadyGrabbed [illegible] DeviceBusy [illegible]

[illegible] Success [illegible]

```
typedef struct {
     XID control;
     int length;
} XDeviceControl;
```

[illegible] < X11/extensions/XI.h > [illegible]

[illegible] XDeviceResolutionControl [illegible]

```
typedef struct {
     XID control;
```

```
    int length;
    int first_valuator;
    int num_valuators;
    int *resolutions;
} XDeviceResolutionControl;
```

[illegible]

[illegible] XChangeDeviceControl [illegible] BadMatch [illegible] XGetDeviceControl), [illegible] XChangeDeviceControl [illegible] BadValue [illegible] BadValue [illegible]

```
    first_valuator + num_valuators,
```

XChangeDeviceControl [illegible] BadMatch [illegible] BadValue [illegible]

Selecting Extension Device Events

[illegible] XSelectExtensionEvent [illegible]

```
int     XSelectExtensionEvent(  *display,    window,    *event_list,
event_count);
```

[illegible]

[illegible]

[illegible]

[illegible]

XSelectExtensionEvent [illegible] XEventClass [illegible] XDevice [illegible] XOpenDevice [illegible] DeviceKeyPress [illegible] XEventClass [illegible] DeviceKeyPress [illegible]

```
DeviceKeyPress (XDevice *device, event_type, event_class)
```

□□□□□□□□□□□□□*□□□□□*□□□□□□*□□□□□□□□□□+□□□□□□□□□□□7

```
DeviceKeyPress
DeviceKeyRelease
DeviceButtonPress
DeviceButtonRelease
DeviceMotionNotify
DeviceFocusIn
DeviceFocusOut
ProximityIn
ProximityOut
DeviceStateNotify
DeviceMappingNotify
ChangeDeviceNotify
DevicePointerMotionHint
DeviceButton1Motion
DeviceButton2Motion
DeviceButton3Motion,
DeviceButton4Motion
DeviceButton5Motion
DeviceButtonMotion,
DeviceOwnerGrabButton
DeviceButtonPressGrab
```

8□□□□□□□□□□□□.□□□+□□□□□□□□□+□□□□*□□'□□□□□□□□□□□□□□□□□□$□□□□□'□□)□□XNex+□□□□□tEvent□*)□□□□□□!□8□□□□□□□)□□□□□□□□□.□□□+□□□□□□□□□□□□□□□□□'□□*□□'□□□□□□□□□□+□□□□□□□□□□.□□□□□□□□□□+□□□!

□)□□□□□□□□□ XSelectExtensionEvent□□□G)□□□□□)□□□□□□+□□□□□□□□□□□□*□□□□□□□□□'□□□+□□□□□□□□□□□□$□□□*□□□□□□□□□$□□+□□)□□□□G)□□□□□□□□□□□$□□□□□□□□□$□□+□□)□□□□□□□*□□□□□□□□□□□+□□□□□*□□'□□□□□□□□+□□□□□□□□□□□□□□□□□□□□□!

XSelectExtensionEvent□□□□□□□□□□□□□□BadAccess , □BadClass ,□BadLength , □□□□BadWindow□□□□□□□!

Determining Selected Device Events

8□□□□□□□'□□□□□□□□□□□□.□□□□□□□□□+□□□□□□□□□□)□□□□□□□□□□□□□□□□□□*□□'□□□□□+□□□□□□□□□□□)□□□XGetSelectedExtensionEvents .

```
int        XGetSelectedExtensionEvents(   *display,       window,
*this_client_count,        **this_client,        *all_clients_count,
**all_clients);
```

□$□□□*□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□!

□$□□□*□□□□□□□□,=□□*□□□□□□□□□□□□*□□'□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□+□□□+□□□□!

□□□)□□□□□□□□)'□□□□*□□□'□□□□□□□□□□□□□□□□□□L□□□□□□□□□□□!

[illegible])[illegible] XEventClasses [illegible]$[illegible]*[illegible] [illegible]+[illegible]!

[illegible])[illegible])'[illegible]*[illegible]'[illegible]L[illegible]!

[illegible])[illegible] XEventClasses [illegible]$[illegible]*[illegible] [illegible]+[illegible]!

XGetSelectedExtensionEvents [illegible])[illegible]$[illegible]+[illegible]!:[illegible].[illegible]+[illegible]*[illegible]'[illegible]$[illegible]*[illegible]!8[illegible].[illegible]+[illegible]*[illegible]'[illegible]$[illegible]*[illegible]!8[illegible]*[illegible]'[illegible])[illegible])[illegible])[illegible]L[illegible]+[illegible]L'[illegible]L[illegible]+[illegible]L'[illegible]*[illegible] XWindowAttributes [illegible])[illegible])[illegible] XGetWindowAttributes [illegible]G)[illegible]'[illegible]!8[illegible]*[illegible])[illegible]*)[illegible] XFree [illegible]!

XGetSelectedExtensionEvents [illegible] BadWindow [illegible]!

Controlling Event Propagation

9.[illegible]+[illegible]$[illegible]$[illegible])$[illegible]'[illegible]'[illegible]+[illegible]!,*[illegible].[illegible]+[illegible])[illegible])[illegible]$[illegible]$[illegible])[illegible]L$[illegible]$[illegible]$[illegible]![illegible]*[illegible].[illegible]+[illegible]'[illegible]*[illegible]+[illegible]$[illegible])[illegible].[illegible]+[illegible]!

#[illegible]$[illegible]'[illegible]'[illegible]+[illegible]$[illegible]$[illegible])[illegible])[illegible]*[illegible]*[illegible]*)[illegible]7 XChangeDeviceDontPropagateList [illegible] XGetDeviceDontPropagateList .

```
int   XChangeDeviceDontPropagateList( *display,   window,   event_count,
*events,   mode);
```

[illegible]$[illegible]*[illegible]+[illegible]!

[illegible]$[illegible]*[illegible]!

[illegible]$[illegible]*[illegible])'[illegible]*[illegible]'[illegible]+[illegible]!

[illegible]$[illegible]*[illegible]$[illegible]*[illegible]9+[illegible]#[illegible]!

[illegible]$[illegible]*[illegible]'[illegible]![illegible]B[illegible])[illegible]$[illegible] AddToList [illegible] DeleteFromList .

XChangeDeviceDontPropagateList [illegible]+[illegible]+[illegible]*[illegible]'[illegible]L[illegible]L$[illegible]$[illegible]*[illegible].[illegible]+[illegible]*[illegible]$[illegible]*[illegible]!8[illegible]$[illegible]'[illegible]*[illegible]*[illegible]*[illegible]!8[illegible]*[illegible]'[illegible]!

[illegible])$$[illegible]*[illegible]+[illegible]$[illegible]$[illegible]*[illegible]+[illegible]!,XEvent[illegible]*[illegible] Class [illegible]+[illegible])[illegible])$$[illegible]*[illegible]+[illegible] BadClass [illegible])[illegible]!

XChangeDeviceDontPropagateList [illegible] BadClass , BadMode , [illegible] BadWindow [illegible]!

```
XEventClass   *   XGetDeviceDontPropagateList(   *display,     window,
*event_count);
```

[illegible]

[illegible]

[illegible]

XGetDeviceDontPropagateList [illegible] XEvent [illegible] Class, [illegible] XEventClass [illegible] XFree!

XGetDeviceDontPropagateList [illegible] BadWindow [illegible]

Sending an Event

[illegible] XSendExtensionEvent.

```
int XSendExtensionEvent( *display, *device, window, propagate,
event_count, *event_list, *event);
```

[illegible]

[illegible]

[illegible] PointerWindow [illegible] InputFocus.

[illegible] True [illegible] False.

[illegible]

[illegible] XEventClass.

[illegible]

XSendExtensionEvent [illegible] XEventClass [illegible] XOpenDevice [illegible]

XSendExtensionEvent [illegible]

[illegible] PointerWindow, [illegible]

[illegible] InputFocus [illegible]

[illegible] XSendExtensionEvent [illegible]

[illegible] False, [illegible]

[illegible] `True` [illegible] `InputFocus` [illegible]

[illegible] `XEvent` [illegible] `True` [illegible]

`XSendExtensionEvent` [illegible]

`XSendExtensionEvent` [illegible] `BadClass`, `BadDevice`, `BadValue`, [illegible] `BadWindow` [illegible]

Getting Motion History

```
XDeviceTimeCoord   *      XGetDeviceMotionEvents(   axis_count_return),
*display,     *device,     stop,     *nevents_return,     *mode_return,
*axis_count_return);
```

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible] `Absolute` [illegible] `Relative`.

[illegible]

`XGetDeviceMotionEvents` [illegible]

[illegible] `XDeviceTimeCoord` [illegible]

```
typedef struct {
```

```
    Time time;
    unsigned int *data;
} XDeviceTimeCoord;
```

[illegible]

[illegible] Absolute, [illegible] XAxisInfo [illegible] XListInputDevices [illegible]

[illegible] Relative, [illegible]

[illegible] XGetDeviceMotionEvents [illegible] XSetDeviceMode [illegible]

XGetDeviceMotionEvents [illegible] BadDevice [illegible] BadMatch [illegible]

[illegible] XGetDeviceMotionEvents, [illegible] XFreeDeviceMotionEvents.

```
void  XFreeDeviceMotionEvents( *events);
```

[illegible] XDeviceTimeCoord [illegible] XGetDeviceMotionEvents.

XFreeDeviceMotionEvents [illegible] Appendix A

[illegible] <X11/extensions/XInput.h> [illegible] <X11/extensions/XI.h> [illegible]

```
/* Definitions used by the library and client */

#ifndef _XINPUT_H_
#define _XINPUT_H_

#ifndef _XLIB_H_
#include <X11/Xlib.h>
#endif

#ifndef _XI_H_
#include "XI.h"
#endif
```

```
#define _deviceKeyPress          0
#define _deviceKeyRelease     1

#define _deviceButtonPress     0
#define _deviceButtonRelease     1

#define _deviceMotionNotify     0

#define _deviceFocusIn          0
#define _deviceFocusOut          1

#define _proximityIn          0
#define _proximityOut          1

#define _deviceStateNotify     0
#define _deviceMappingNotify     1
#define _changeDeviceNotify     2

#define FindTypeAndClass(d, type, class, classid, offset) \
    { int i; XInputClassInfo *ip; \
    type = 0; class = 0; \
    for (i=0, ip= ((XDevice *) d)->classes; \
      i< ((XDevice *) d)->num_classes; \
      i++, ip++) \
     if (ip->input_class == classid) \
         {type =  ip->event_type_base + offset; \
          class =  ((XDevice *) d)->device_id << 8 | type;}}

#define DeviceKeyPress(d, type, class) \
    FindTypeAndClass(d, type, class, KeyClass, _deviceKeyPress)

#define DeviceKeyRelease(d, type, class) \
    FindTypeAndClass(d, type, class, KeyClass, _deviceKeyRelease)

#define DeviceButtonPress(d, type, class) \
    FindTypeAndClass(d, type, class, ButtonClass, _deviceButtonPress)

#define DeviceButtonRelease(d, type, class) \
    FindTypeAndClass(d, type, class, ButtonClass, _deviceButtonRelease)

#define DeviceMotionNotify(d, type, class) \
    FindTypeAndClass(d, type, class, ValuatorClass, _deviceMotionNotify)

#define DeviceFocusIn(d, type, class) \
    FindTypeAndClass(d, type, class, FocusClass, _deviceFocusIn)

#define DeviceFocusOut(d, type, class) \
    FindTypeAndClass(d, type, class, FocusClass, _deviceFocusOut)

#define ProximityIn(d, type, class) \
    FindTypeAndClass(d, type, class, ProximityClass, _proximityIn)

#define ProximityOut(d, type, class) \
```

```
    FindTypeAndClass(d, type, class, ProximityClass, _proximityOut)

#define DeviceStateNotify(d, type, class) \
    FindTypeAndClass(d, type, class, OtherClass, _deviceStateNotify)

#define DeviceMappingNotify(d, type, class) \
    FindTypeAndClass(d, type, class, OtherClass, _deviceMappingNotify)

#define ChangeDeviceNotify(d, type, class) \
    FindTypeAndClass(d, type, class, OtherClass, _changeDeviceNotify)

#define DevicePointerMotionHint(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _devicePointerMotionHint;}

#define DeviceButton1Motion(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceButton1Motion;}

#define DeviceButton2Motion(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceButton2Motion;}

#define DeviceButton3Motion(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceButton3Motion;}

#define DeviceButton4Motion(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceButton4Motion;}

#define DeviceButton5Motion(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceButton5Motion;}

#define DeviceButtonMotion(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceButtonMotion;}

#define DeviceOwnerGrabButton(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceOwnerGrabButton;}

#define DeviceButtonPressGrab(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _deviceButtonGrab;}

#define NoExtensionEvent(d, type, class) \
    { class =  ((XDevice *) d)->device_id << 8 | _noExtensionEvent;}

#define BadDevice(dpy, error) _xibaddevice(dpy, &error)

#define BadClass(dpy, error) _xibadclass(dpy, &error)

#define BadEvent(dpy, error) _xibadevent(dpy, &error)

#define BadMode(dpy, error) _xibadmode(dpy, &error)

#define DeviceBusy(dpy, error) _xidevicebusy(dpy, &error)

/***************************************************************
 *
 * DeviceKey events.  These events are sent by input devices that
```

```
 * support input class Keys.
 * The location of the X pointer is reported in the coordinate
 * fields of the x,y and x_root,y_root fields.
 *
 */

typedef struct
    {
    int             type;          /* of event */
    unsigned long   serial;        /* # of last request processed */
    Bool            send_event;    /* true if from SendEvent request */
    Display         *display;      /* Display the event was read from */
    Window          window;        /* "event" window reported relative to */
    XID             deviceid;
    Window          root;          /* root window event occured on */
    Window          subwindow;     /* child window */
    Time            time;          /* milliseconds */
    int             x, y;          /* x, y coordinates in event window */
    int             x_root;        /* coordinates relative to root */
    int             y_root;        /* coordinates relative to root */
    unsigned int    state;         /* key or button mask */
    unsigned int    keycode;       /* detail */
    Bool            same_screen;   /* same screen flag */
    unsigned int    device_state;  /* device key or button mask */
    unsigned char   axes_count;
    unsigned char   first_axis;
    int             axis_data[6];
    } XDeviceKeyEvent;

typedef XDeviceKeyEvent XDeviceKeyPressedEvent;
typedef XDeviceKeyEvent XDeviceKeyReleasedEvent;

/*******************************************************************
 *
 * DeviceButton events.  These events are sent by extension devices
 * that support input class Buttons.
 *
 */

typedef struct {
    int           type;          /* of event */
    unsigned long serial;        /* # of last request processed by server */
    Bool          send_event;    /* true if from a SendEvent request */
    Display       *display;      /* Display the event was read from */
    Window        window;        /* "event" window reported relative to */
    XID           deviceid;
    Window        root;          /* root window that the event occured on */
    Window        subwindow;     /* child window */
    Time          time;          /* milliseconds */
    int           x, y;          /* x, y coordinates in event window */
    int           x_root;        /* coordinates relative to root */
    int           y_root;        /* coordinates relative to root */
    unsigned int  state;         /* key or button mask */
    unsigned int  button;        /* detail */
```

```
    Bool          same_screen;  /* same screen flag */
    unsigned int  device_state; /* device key or button mask */
    unsigned char axes_count;
    unsigned char first_axis;
    int           axis_data[6];
    } XDeviceButtonEvent;

typedef XDeviceButtonEvent XDeviceButtonPressedEvent;
typedef XDeviceButtonEvent XDeviceButtonReleasedEvent;

/*******************************************************************
 *
 * DeviceMotionNotify event.  These events are sent by extension devices
 * that support input class Valuators.
 *
 */

typedef struct
    {
    int           type;        /* of event */
    unsigned long serial;      /* # of last request processed by server */
    Bool          send_event;  /* true if from a SendEvent request */
    Display       *display;    /* Display the event was read from */
    Window        window;      /* "event" window reported relative to */
    XID           deviceid;
    Window        root;        /* root window that the event occured on */
    Window        subwindow;   /* child window */
    Time          time;        /* milliseconds */
    int           x, y;        /* x, y coordinates in event window */
    int           x_root;      /* coordinates relative to root */
    int           y_root;      /* coordinates relative to root */
    unsigned int  state;       /* key or button mask */
    char          is_hint;     /* detail */
    Bool          same_screen; /* same screen flag */
    unsigned int  device_state; /* device key or button mask */
    unsigned char axes_count;
    unsigned char first_axis;
    int           axis_data[6];
    } XDeviceMotionEvent;

/*******************************************************************
 *
 * DeviceFocusChange events.  These events are sent when the focus
 * of an extension device that can be focused is changed.
 *
 */

typedef struct
    {
    int           type;       /* of event */
    unsigned long serial;     /* # of last request processed by server */
    Bool          send_event; /* true if from a SendEvent request */
    Display       *display;   /* Display the event was read from */
    Window        window;     /* "event" window reported relative to */
```

```
    XID           deviceid;
    int           mode;       /* NotifyNormal, NotifyGrab, NotifyUngrab */
    int           detail;
     /*
      * NotifyAncestor, NotifyVirtual, NotifyInferior,
      * NotifyNonLinear,NotifyNonLinearVirtual, NotifyPointer,
      * NotifyPointerRoot, NotifyDetailNone
      */
    Time                time;
    } XDeviceFocusChangeEvent;

typedef XDeviceFocusChangeEvent XDeviceFocusInEvent;
typedef XDeviceFocusChangeEvent XDeviceFocusOutEvent;

/*******************************************************************
 *
 * ProximityNotify events.  These events are sent by those absolute
 * positioning devices that are capable of generating proximity information.
 *
 */

typedef struct
    {
    int             type;      /* ProximityIn or ProximityOut */
    unsigned long   serial;    /* # of last request processed by server */
    Bool            send_event; /* true if this came from a SendEvent request */
    Display         *display;  /* Display the event was read from */
    Window          window;
    XID                 deviceid;
    Window          root;
    Window          subwindow;
    Time            time;
    int             x, y;
    int             x_root, y_root;
    unsigned int    state;
    Bool            same_screen;
    unsigned int    device_state; /* device key or button mask */
    unsigned char   axes_count;
    unsigned char   first_axis;
    int             axis_data[6];
    } XProximityNotifyEvent;
typedef XProximityNotifyEvent XProximityInEvent;
typedef XProximityNotifyEvent XProximityOutEvent;

/*******************************************************************
 *
 * DeviceStateNotify events are generated on EnterWindow and FocusIn
 * for those clients who have selected DeviceState.
 *
 */

typedef struct
    {
    unsigned char     class;
```

```
    unsigned char     length;
    } XInputClass;

typedef struct {
    int           type;
    unsigned long serial;       /* # of last request processed by server */
    Bool          send_event;   /* true if this came from a SendEvent request */
    Display       *display;     /* Display the event was read from */
    Window        window;
    XID           deviceid;
    Time          time;
    int           num_classes;
    char       data[64];
} XDeviceStateNotifyEvent;

typedef struct {
    unsigned char     class;
    unsigned char     length;
    unsigned char     num_valuators;
    unsigned char     mode;
    int                  valuators[6];
} XValuatorStatus;

typedef struct {
    unsigned char     class;
    unsigned char     length;
    short          num_keys;
    char             keys[32];
} XKeyStatus;

typedef struct {
    unsigned char     class;
    unsigned char     length;
    short          num_buttons;
    char             buttons[32];
} XButtonStatus;

/*******************************************************************
 *
 * DeviceMappingNotify event.  This event is sent when the key mapping,
 * modifier mapping, or button mapping of an extension device is changed.
 *
 */

typedef struct {
    int           type;
    unsigned long serial;       /* # of last request processed by server */
    Bool          send_event;   /* true if this came from a SendEvent request */
    Display       *display;     /* Display the event was read from */
    Window        window;       /* unused */
    XID           deviceid;
    Time          time;
    int           request;      /* one of MappingModifier, MappingKeyboard,
                                    MappingPointer */
```

```
    int           first_keycode;/* first keycode */
    int           count;        /* defines range of change w. first_keycode*/
} XDeviceMappingEvent;

/*******************************************************************
 *
 * ChangeDeviceNotify event.  This event is sent when an
 * XChangeKeyboard or XChangePointer request is made.
 *
 */

typedef struct {
    int           type;
    unsigned long serial;       /* # of last request processed by server */
    Bool          send_event;   /* true if this came from a SendEvent request */
    Display       *display;     /* Display the event was read from */
    Window        window;       /* unused */
    XID           deviceid;
    Time          time;
    int           request;      /* NewPointer or NewKeyboard */
} XChangeDeviceNotifyEvent;

/*******************************************************************
 *
 * Control structures for input devices that support input class
 * Feedback.  These are used by the XGetFeedbackControl and
 * XChangeFeedbackControl functions.
 *
 */

typedef struct {
     XID            class;
     int            length;
     XID            id;
} XFeedbackState;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     click;
    int     percent;
    int     pitch;
    int     duration;
    int     led_mask;
    int     global_auto_repeat;
    char    auto_repeats[32];
} XKbdFeedbackState;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     accelNum;
```

```
    int     accelDenom;
    int     threshold;
} XPtrFeedbackState;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     resolution;
    int     minVal;
    int     maxVal;
} XIntegerFeedbackState;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     max_symbols;
    int     num_syms_supported;
    KeySym  *syms_supported;
} XStringFeedbackState;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     percent;
    int     pitch;
    int     duration;
} XBellFeedbackState;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     led_values;
    int     led_mask;
} XLedFeedbackState;

typedef struct {
     XID            class;
     int            length;
     XID         id;
} XFeedbackControl;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     accelNum;
    int     accelDenom;
    int     threshold;
} XPtrFeedbackControl;
```

```
typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     click;
    int     percent;
    int     pitch;
    int     duration;
    int     led_mask;
    int     led_value;
    int     key;
    int     auto_repeat_mode;
} XKbdFeedbackControl;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     num_keysyms;
    KeySym  *syms_to_display;
} XStringFeedbackControl;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     int_to_display;
} XIntegerFeedbackControl;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     percent;
    int     pitch;
    int     duration;
} XBellFeedbackControl;

typedef struct {
    XID     class;
    int     length;
    XID     id;
    int     led_mask;
    int     led_values;
} XLedFeedbackControl;

/*******************************************************************
 *
 * Device control structures.
 *
 */

typedef struct {
     XID            control;
```

```
     int            length;
} XDeviceControl;

typedef struct {
     XID            control;
     int            length;
     int            first_valuator;
     int            num_valuators;
     int            *resolutions;
} XDeviceResolutionControl;

typedef struct {
     XID            control;
     int            length;
     int            num_valuators;
     int            *resolutions;
     int            *min_resolutions;
     int            *max_resolutions;
} XDeviceResolutionState;

/*******************************************************************
 *
 * An array of XDeviceList structures is returned by the
 * XListInputDevices function.  Each entry contains information
 * about one input device.  Among that information is an array of
 * pointers to structures that describe the characteristics of
 * the input device.
 *
 */

typedef struct _XAnyClassinfo *XAnyClassPtr;

typedef struct _XAnyClassinfo {
    XID      class;
    int      length;
    } XAnyClassInfo;

typedef struct _XDeviceInfo *XDeviceInfoPtr;

typedef struct _XDeviceInfo
    {
    XID                 id;
    Atom                type;
    char                *name;
    int                 num_classes;
    int                 use;
    XAnyClassPtr      inputclassinfo;
    } XDeviceInfo;

typedef struct _XKeyInfo *XKeyInfoPtr;

typedef struct _XKeyInfo
    {
    XID               class;
```

```
    int               length;
    unsigned short      min_keycode;
    unsigned short      max_keycode;
    unsigned short      num_keys;
    } XKeyInfo;

typedef struct _XButtonInfo *XButtonInfoPtr;

typedef struct _XButtonInfo {
    XID          class;
    int          length;
    short      num_buttons;
    } XButtonInfo;

typedef struct _XAxisInfo *XAxisInfoPtr;

typedef struct _XAxisInfo {
    int      resolution;
    int      min_value;
    int      max_value;
    } XAxisInfo;

typedef struct _XValuatorInfo *XValuatorInfoPtr;

typedef struct     _XValuatorInfo
    {
    XID               class;
    int               length;
    unsigned char       num_axes;
    unsigned char       mode;
    unsigned long       motion_buffer;
    XAxisInfoPtr        axes;
    } XValuatorInfo;


/*******************************************************************
 *
 * An XDevice structure is returned by the XOpenDevice function.
 * It contains an array of pointers to XInputClassInfo structures.
 * Each contains information about a class of input supported by the
 * device, including a pointer to an array of data for each type of event
 * the device reports.
 *
 */


typedef struct {
        unsigned char   input_class;
        unsigned char   event_type_base;
} XInputClassInfo;

typedef struct {
        XID                    device_id;
        int                    num_classes;
```

```
        XInputClassInfo        *classes;
} XDevice;


/*******************************************************************
 *
 * The following structure is used to return information for the
 * XGetSelectedExtensionEvents function.
 *
 */

typedef struct {
        XEventClass     event_type;
        XID             device;
} XEventList;

/*******************************************************************
 *
 * The following structure is used to return motion history data from
 * an input device that supports the input class Valuators.
 * This information is returned by the XGetDeviceMotionEvents function.
 *
 */

typedef struct {
        Time   time;
        int    *data;
} XDeviceTimeCoord;


/*******************************************************************
 *
 * Device state structure.
 * This is returned by the XQueryDeviceState request.
 *
 */

typedef struct {
        XID          device_id;
        int          num_classes;
        XInputClass     *data;
} XDeviceState;

/*******************************************************************
 *
 * Note that the mode field is a bitfield that reports the Proximity
 * status of the device as well as the mode.  The mode field should
 * be OR'd with the mask DeviceMode and compared with the values
 * Absolute and Relative to determine the mode, and should be OR'd
 * with the mask ProximityState and compared with the values InProximity
 * and OutOfProximity to determine the proximity state.
 *
 */
```

```
typedef struct {
    unsigned char     class;
    unsigned char     length;
    unsigned char     num_valuators;
    unsigned char     mode;
    int                  *valuators;
} XValuatorState;

typedef struct {
    unsigned char     class;
    unsigned char     length;
    short          num_keys;
    char             keys[32];
} XKeyState;

typedef struct {
    unsigned char     class;
    unsigned char     length;
    short          num_buttons;
    char             buttons[32];
} XButtonState;

/*******************************************************************
 *
 * Function definitions.
 *
 */

_XFUNCPROTOBEGIN

extern int     XChangeKeyboardDevice(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */
#endif
);

extern int     XChangePointerDevice(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int               /* xaxis */,
    int               /* yaxis */
#endif
);

extern int     XGrabDevice(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    Window          /* grab_window */,
    Bool          /* ownerEvents */,
    int               /* event count */,
    XEventClass*     /* event_list */,
```

```
    int               /* this_device_mode */,
    int               /* other_devices_mode */,
    Time          /* time */
#endif
);

extern int     XUngrabDevice(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    Time           /* time */
#endif
);

extern int     XGrabDeviceKey(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    unsigned int     /* key */,
    unsigned int     /* modifiers */,
    XDevice*          /* modifier_device */,
    Window          /* grab_window */,
    Bool          /* owner_events */,
    unsigned int     /* event_count */,
    XEventClass*     /* event_list */,
    int               /* this_device_mode */,
    int               /* other_devices_mode */
#endif
);

extern int     XUngrabDeviceKey(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    unsigned int     /* key */,
    unsigned int     /* modifiers */,
    XDevice*          /* modifier_dev */,
    Window          /* grab_window */
#endif
);

extern int     XGrabDeviceButton(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    unsigned int     /* button */,
    unsigned int     /* modifiers */,
    XDevice*          /* modifier_device */,
    Window          /* grab_window */,
    Bool          /* owner_events */,
    unsigned int     /* event_count */,
    XEventClass*     /* event_list */,
    int               /* this_device_mode */,
    int               /* other_devices_mode */
```

```
#endif
);

extern int     XUngrabDeviceButton(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    unsigned int     /* button */,
    unsigned int     /* modifiers */,
    XDevice*          /* modifier_dev */,
    Window          /* grab_window */
#endif
);

extern int     XAllowDeviceEvents(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int               /* event_mode */,
    Time          /* time */
#endif
);

extern int     XGetDeviceFocus(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    Window*          /* focus */,
    int*          /* revert_to */,
    Time*          /* time */
#endif
);

extern int     XSetDeviceFocus(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    Window          /* focus */,
    int               /* revert_to */,
    Time          /* time */
#endif
);

extern XFeedbackState     *XGetFeedbackControl(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int*          /* num_feedbacks */
#endif
);

extern int     XFreeFeedbackList(
#if NeedFunctionPrototypes
    XFeedbackState*     /* list */
```

```
#endif
);

extern int     XChangeFeedbackControl(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    unsigned long     /* mask */,
    XFeedbackControl*     /* f */
#endif
);

extern int     XDeviceBell(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    XID               /* feedbackclass */,
    XID               /* feedbackid */,
    int               /* percent */
#endif
);

extern KeySym     *XGetDeviceKeyMapping(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
#if NeedWidePrototypes
    unsigned int     /* first */,
#else
    KeyCode          /* first */,
#endif
    int               /* keycount */,
    int*          /* syms_per_code */
#endif
);

extern int     XChangeDeviceKeyMapping(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int               /* first */,
    int               /* syms_per_code */,
    KeySym*          /* keysyms */,
    int               /* count */
#endif
);

extern XModifierKeymap     *XGetDeviceModifierMapping(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */
#endif
);
```

```
extern int     XSetDeviceModifierMapping(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    XModifierKeymap*     /* modmap */
#endif
);

extern int     XSetDeviceButtonMapping(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    unsigned char*     /* map[] */,
    int               /* nmap */
#endif
);

extern int     XGetDeviceButtonMapping(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    unsigned char*     /* map[] */,
    unsigned int     /* nmap */
#endif
);

extern XDeviceState     *XQueryDeviceState(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */
#endif
);

extern int     XFreeDeviceState(
#if NeedFunctionPrototypes
    XDeviceState*     /* list */
#endif
);

extern XExtensionVersion *XGetExtensionVersion(
#if NeedFunctionPrototypes
    Display*          /* display */,
    _Xconst char*     /* name */
#endif
);

extern XDeviceInfo     *XListInputDevices(
#if NeedFunctionPrototypes
    Display*          /* display */,
    int*          /* ndevices */
#endif
);

extern int     XFreeDeviceList(
```

```
#if NeedFunctionPrototypes
    XDeviceInfo*     /* list */
#endif
);

extern XDevice     *XOpenDevice(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XID               /* id */
#endif
);

extern int     XCloseDevice(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */
#endif
);

extern int     XSetDeviceMode(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int               /* mode */
#endif
);

extern int     XSetDeviceValuators(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int*          /* valuators */,
    int               /* first_valuator */,
    int               /* num_valuators */
#endif
);

extern XDeviceControl     *XGetDeviceControl(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int               /* control */
#endif
);

extern int     XChangeDeviceControl(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    int               /* control */,
    XDeviceControl*     /* d */
#endif
);
```

```
extern int      XSelectExtensionEvent(
#if NeedFunctionPrototypes
    Display*          /* display */,
    Window          /* w */,
    XEventClass*     /* event_list */,
    int               /* count */
#endif
);

extern int      XGetSelectedExtensionEvents(
#if NeedFunctionPrototypes
    Display*          /* display */,
    Window          /* w */,
    int*          /* this_client_count */,
    XEventClass**     /* this_client_list */,
    int*          /* all_clients_count */,
    XEventClass**     /* all_clients_list */
#endif
);

extern int      XChangeDeviceDontPropagateList(
#if NeedFunctionPrototypes
    Display*          /* display */,
    Window          /* window */,
    int               /* count */,
    XEventClass*     /* events */,
    int               /* mode */
#endif
);

extern XEventClass      *XGetDeviceDontPropagateList(
#if NeedFunctionPrototypes
    Display*          /* display */,
    Window          /* window */,
    int*          /* count */
#endif
);

extern Status      XSendExtensionEvent(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
    Window          /* dest */,
    Bool          /* prop */,
    int               /* count */,
    XEventClass*     /* list */,
    XEvent*          /* event */
#endif
);

extern XDeviceTimeCoord     *XGetDeviceMotionEvents(
#if NeedFunctionPrototypes
    Display*          /* display */,
    XDevice*          /* device */,
```

```
    Time          /* start */,
    Time          /* stop */,
    int*          /* nEvents */,
    int*          /* mode */,
    int*          /* axis_count */
#endif
);

extern int     XFreeDeviceMotionEvents(
#if NeedFunctionPrototypes
    XDeviceTimeCoord*     /* events */
#endif
);

extern int     XFreeDeviceControl(
#if NeedFunctionPrototypes
    XDeviceControl*     /* control */
#endif
);

_XFUNCPROTOEND

#endif /* _XINPUT_H_ */

/* Definitions used by the server, library and client */

#ifndef _XI_H_

#define _XI_H_

#define sz_xGetExtensionVersionReq          8
#define sz_xGetExtensionVersionReply          32
#define sz_xListInputDevicesReq               4
#define sz_xListInputDevicesReply          32
#define sz_xOpenDeviceReq               8
#define sz_xOpenDeviceReply               32
#define sz_xCloseDeviceReq               8
#define sz_xSetDeviceModeReq               8
#define sz_xSetDeviceModeReply               32
#define sz_xSelectExtensionEventReq          12
#define sz_xGetSelectedExtensionEventsReq     8
#define sz_xGetSelectedExtensionEventsReply     32
#define sz_xChangeDeviceDontPropagateListReq     12
#define sz_xGetDeviceDontPropagateListReq     8
#define sz_xGetDeviceDontPropagateListReply     32
#define sz_xGetDeviceMotionEventsReq          16
#define sz_xGetDeviceMotionEventsReply          32
#define sz_xChangeKeyboardDeviceReq          8
#define sz_xChangeKeyboardDeviceReply          32
#define sz_xChangePointerDeviceReq          8
#define sz_xChangePointerDeviceReply          32
#define sz_xGrabDeviceReq               20
#define sz_xGrabDeviceReply               32
#define sz_xUngrabDeviceReq               12
```

```
#define sz_xGrabDeviceKeyReq               20
#define sz_xGrabDeviceKeyReply               32
#define sz_xUngrabDeviceKeyReq               16
#define sz_xGrabDeviceButtonReq               20
#define sz_xGrabDeviceButtonReply          32
#define sz_xUngrabDeviceButtonReq          16
#define sz_xAllowDeviceEventsReq          12
#define sz_xGetDeviceFocusReq               8
#define sz_xGetDeviceFocusReply               32
#define sz_xSetDeviceFocusReq               16
#define sz_xGetFeedbackControlReq          8
#define sz_xGetFeedbackControlReply          32
#define sz_xChangeFeedbackControlReq          12
#define sz_xGetDeviceKeyMappingReq          8
#define sz_xGetDeviceKeyMappingReply          32
#define sz_xChangeDeviceKeyMappingReq          8
#define sz_xGetDeviceModifierMappingReq          8
#define sz_xSetDeviceModifierMappingReq          8
#define sz_xSetDeviceModifierMappingReply     32
#define sz_xGetDeviceButtonMappingReq          8
#define sz_xGetDeviceButtonMappingReply          32
#define sz_xSetDeviceButtonMappingReq          8
#define sz_xSetDeviceButtonMappingReply          32
#define sz_xQueryDeviceStateReq               8
#define sz_xQueryDeviceStateReply          32
#define sz_xSendExtensionEventReq          16
#define sz_xDeviceBellReq               8
#define sz_xSetDeviceValuatorsReq          8
#define sz_xSetDeviceValuatorsReply          32
#define sz_xGetDeviceControlReq               8
#define sz_xGetDeviceControlReply          32
#define sz_xChangeDeviceControlReq          8
#define sz_xChangeDeviceControlReply          32

#define INAME                "XInputExtension"

#define XI_KEYBOARD     "KEYBOARD"
#define XI_MOUSE     "MOUSE"
#define XI_TABLET     "TABLET"
#define XI_TOUCHSCREEN     "TOUCHSCREEN"
#define XI_TOUCHPAD     "TOUCHPAD"
#define XI_BARCODE     "BARCODE"
#define XI_BUTTONBOX     "BUTTONBOX"
#define XI_KNOB_BOX     "KNOB_BOX"
#define XI_ONE_KNOB     "ONE_KNOB"
#define XI_NINE_KNOB     "NINE_KNOB"
#define XI_TRACKBALL     "TRACKBALL"
#define XI_QUADRATURE     "QUADRATURE"
#define XI_ID_MODULE     "ID_MODULE"
#define XI_SPACEBALL     "SPACEBALL"
#define XI_DATAGLOVE     "DATAGLOVE"
#define XI_EYETRACKER     "EYETRACKER"
#define XI_CURSORKEYS     "CURSORKEYS"
#define XI_FOOTMOUSE     "FOOTMOUSE"
```

```
#define Dont_Check               0
#define XInput_Initial_Release          1
#define XInput_Add_XDeviceBell          2
#define XInput_Add_XSetDeviceValuators     3
#define XInput_Add_XChangeDeviceControl     4

#define XI_Absent          0
#define XI_Present          1

#define XI_Initial_Release_Major          1
#define XI_Initial_Release_Minor          0

#define XI_Add_XDeviceBell_Major          1
#define XI_Add_XDeviceBell_Minor          1

#define XI_Add_XSetDeviceValuators_Major     1
#define XI_Add_XSetDeviceValuators_Minor     2

#define XI_Add_XChangeDeviceControl_Major     1
#define XI_Add_XChangeDeviceControl_Minor     3

#define DEVICE_RESOLUTION     1

#define NoSuchExtension          1

#define COUNT               0
#define CREATE               1

#define NewPointer          0
#define NewKeyboard          1

#define XPOINTER          0
#define XKEYBOARD          1

#define UseXKeyboard          0xFF

#define IsXPointer          0
#define IsXKeyboard          1
#define IsXExtensionDevice     2

#define AsyncThisDevice          0
#define SyncThisDevice          1
#define ReplayThisDevice     2
#define AsyncOtherDevices     3
#define AsyncAll          4
#define SyncAll               5

#define FollowKeyboard           3
#define RevertToFollowKeyboard      3

#define DvAccelNum              (1L << 0)
#define DvAccelDenom            (1L << 1)
#define DvThreshold             (1L << 2)
```

```
#define DvKeyClickPercent     (1L<<0)
#define DvPercent          (1L<<1)
#define DvPitch               (1L<<2)
#define DvDuration          (1L<<3)
#define DvLed               (1L<<4)
#define DvLedMode          (1L<<5)
#define DvKey               (1L<<6)
#define DvAutoRepeatMode     (1L<<7)

#define DvString                (1L << 0)

#define DvInteger               (1L << 0)

#define DeviceMode              (1L << 0)
#define Relative                0
#define Absolute                1

#define ProximityState          (1L << 1)
#define InProximity             (0L << 1)
#define OutOfProximity          (1L << 1)

#define AddToList               0
#define DeleteFromList          1

#define KeyClass            0
#define ButtonClass            1
#define ValuatorClass            2
#define FeedbackClass            3
#define ProximityClass       4
#define FocusClass            5
#define OtherClass            6

#define KbdFeedbackClass       0
#define PtrFeedbackClass       1
#define StringFeedbackClass       2
#define IntegerFeedbackClass       3
#define LedFeedbackClass       4
#define BellFeedbackClass       5

#define _devicePointerMotionHint 0
#define _deviceButton1Motion      1
#define _deviceButton2Motion      2
#define _deviceButton3Motion      3
#define _deviceButton4Motion      4
#define _deviceButton5Motion      5
#define _deviceButtonMotion      6
#define _deviceButtonGrab      7
#define _deviceOwnerGrabButton      8
#define _noExtensionEvent      9

#define XI_BadDevice     0
#define XI_BadEvent     1
#define XI_BadMode     2
```

```
#define XI_DeviceBusy     3
#define XI_BadClass     4

typedef     unsigned long     XEventClass;

/*******************************************************************
 *
 * Extension version structure.
 *
 */

typedef struct {
        int        present;
        short     major_version;
        short     minor_version;
} XExtensionVersion;

#endif /* _XI_H_ */
```

Appendix A. Input Extension Protocol Encoding

Syntactic Conventions

[illegible]

[illegible]

```
NameofThing
  encode-form
  ...
  encode-form
```

[illegible]

[illegible]

```
name: TYPE
```

[illegible]

```
N TYPE name
```

[illegible]

```
depth: CARD8
```

[illegible]

```
1 CARD8 depth
```

[illegible]

```
N value name
```

[illegible]

```
1 0 Error
1 3 code
```

[illegible]

```
name: {Name1, ..., NameI}
```

[illegible]

```
N  name
 value1 Name1
 ...
 valueI NameI
```

[illegible]

```
class: {InputOutput, InputOnly, CopyFromParent}
```

[illegible]

```
2   class
 0 CopyFromParent
 1 InputOutput
 2 InputOnly
```

[illegible]

```
NAME: TYPE or Alternative1 ... or AlternativeI
```

[illegible]

```
N TYPE   NAME
 value1 Alternative1
 ...
 valueI AlternativeI
```

[illegible]

```
destination: WINDOW or PointerWindow or InputFocus
```

[illegible]

```
4 WINDOW  destination
 0 PointerWindow
 1 InputFocus
```

[illegible]

```
value-mask: BITMASK
```

[illegible]

```
N BITMASK   value-mask
 mask1 mask-name1
 ...
 maskI mask-nameI
```

[illegible]

[illegible]

```
VALUEs
 encode-form
 ...
 encode-form
```

[illegible]

[illegible]

[illegible]

```
2 3+n   request length
4n LISTofPOINT  points
```

[illegible]

```
N   unused
```

[illegible]

```
p   unused, p=pad(E)
```

[illegible]

```
pad(E) = (4 - (E mod 4)) mod 4
```

Common Types

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

#(□=□R7□□R□□□□□)□□□□□□□□□□□□□□□□

#(□=J07□J0□□□□□)□□□□□□□□□□□□□□□□

8,□9□8(□□7□#(□=J0

9□9A8#D(□□7□#(□=J0

```
INPUTCLASS
 0 KeyClass
 1 ButtonClass
 2 ValuatorClass
 3 FeedbackClass
 4 ProximityClass
 5 FocusClass
 6 OtherClass
```

```
INPUTCLASS
 0 KbdFeedbackClass
 1 PtrFeedbackClass
 2 StringFeedbackClass
 3 IntegerFeedbackClass
 4 LedFeedbackClass
 5 BellFeedbackClass
```

```
INPUTINFO
 0 KEYINFO
 1 BUTTONINFO
 2 VALUATORINFO
```

```
DEVICEMODE
 0 Relative
 1 Absolute
```

```
PROXIMITYSTATE
 0 InProximity
 1 OutOfProximity
```

```
BOOL
 0 False
 1 True
```

C9BB7#(=J0

C9B#:=97#(=&

E@88:A7#(=&

```
SETofKEYBUTMASK
 #x0001 Shift
 #x0002 Lock
 #x0004 Control
 #x0008 Mod1
 #x0010 Mod2
 #x0020 Mod3
 #x0040 Mod4
 #x0080 Mod5
 #x0100 Button1
 #x0200 Button2
 #x0400 Button3
 #x0800 Button4
 #x1000 Button5
 #xe000 unused but must be zero
```

```
SETofKEYMASK
 encodings are the same as for SETofKEYBUTMASK, except with
 #xff00  unused but must be zero
```

8,A&7D,8*#(=&

```
STR
 1 n  length of name in bytes
 n STRING8  name
```

Errors

```
Request
 1 0  Error
 1 1  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
```

```
 1 CARD8  major opcode
 21   unused




Value
 1 0  Error
 1 2  code
 2 CARD16  sequence number
 4 <32-bits>  bad value
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Window
 1 0  Error
 1 3  code
 2 CARD16  sequence number
 4 CARD32  bad resource id
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Match
 1 0  Error
 1 8  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Access
 1 0  Error
 1 10  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Alloc
```

```
 1 0  Error
 1 11  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Name
 1 0  Error
 1 15  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Device
 1 0  Error
 1 CARD8  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Event
 1 0  Error
 1 CARD8  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused




Mode
 1 0  Error
 1 CARD8  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused
```

```
Class
 1 0  Error
 1 CARD8  code
 2 CARD16  sequence number
 4   unused
 2 CARD16  minor opcode
 1 CARD8  major opcode
 21   unused
```

C[illegible]

C9B#:=9[illegible]+[illegible])[illegible] [illegible]1[illegible]0TR4!

C9B[illegible]B[illegible]+[illegible])[illegible]U.[illegible]""""""""[illegible]+[illegible]+[illegible]$[illegible]*[illegible]!

8[illegible]'[illegible]*[illegible]C9B[illegible]B[illegible]+[illegible])[illegible]$$[illegible].
;!

[illegible]

E@88:A[illegible]+[illegible])[illegible])'[illegible]!

[illegible]G)[illegible]

```
GetExtensionVersion
 1 CARD8  input extension opcode
 1 1  GetExtensionVersion opcode
 2 2+(n+p)/4  request length
 2 n  length of name
 2   unused
 n STRING8  name
 p   unused, p=pad(n)
```

```
 =>
 1 1  Reply
 1 1  GetExtensionVersion opcode
 2 CARD16  sequence number
 4 0  reply length
 2 CARD16  major version
 2 CARD16  minor version
 1 BOOL  present
 19   unused
```

```
ListInputDevices
```

```
1 CARD8  input extension opcode
1 2  ListInputDevices opcode
2 1  request length
```

```
=>
1 1   Reply
1 2   ListInputDevices opcode
2 CARD16   sequence number
4 (n+p)/4   reply length
1 CARD8   number of input devices
23    unused
n LISTofDEVICEINFO info for each input device
p    unused, p=pad(n)
```

```
 DEVICEINFO
4 CARD32  device type
1 CARD8  device id
1 CARD8  number of input classes this device reports
1 CARD8  device use
  0 IsXPointer
  1 IsXKeyboard
  2 IsXExtensionDevice
1   unused
n LISTofINPUTINFO   input info for each input class
m STR   name
p    unused, p=pad(m)
```

```
 INPUTINFO KEYINFO or BUTTONINFO or VALUATORINFO
```

```
 KEYINFO
1 0  class id
1 8  length
1 KEYCODE  minimum keycode
1 KEYCODE  maximum keycode
2 CARD16  number of keys
2   unused
```

```
BUTTONINFO
 1 1  class id
 1 4  length
```

```
 2 CARD16  number of buttons




VALUATORINFO
 1 2  class id
 1 8+12n  length
 1 n  number of axes
 1 SETofDEVICEMODE   mode
 4 CARD32  size of motion buffer
 12n LISTofAXISINFO  valuator limits




AXISINFO
 4 CARD32  resolution
 4 CARD32  minimum value
 4 CARD32  maximum value




OpenDevice
 1 CARD8  input extension opcode
 1 3  OpenDevice opcode
 2 2  request length
 1 CARD8  device id
 3   unused




 =>
 1 1   Reply
 1 3   OpenDevice opcode
 2 CARD16   sequence number
 4 (n+p)/4   reply length
 1 CARD8   number of input classes
 23    unused
 n LISTofINPUTCLASSINFO input class information
 p    unused, p=pad(n)




  INPUTCLASSINFO
 1 CARD8  input class id
  0 KEY
  1 BUTTON
  2 VALUATOR
  3 FEEDBACK
  4 PROXIMITY
  5 FOCUS
```

```
  6 OTHER
 1 CARD8  event type base code for this class
```

```
CloseDevice
 1 CARD8  input extension opcode
 1 4  CloseDevice opcode
 2 2  request length
 1 CARD8  device id
 3   unused
```

```
SetDeviceMode
 1 CARD8  input extension opcode
 1 5  SetDeviceMode opcode
 2 2  request length
 1 CARD8  device id
 1 CARD8  mode
 2   unused
```

```
 =>
 1 1   Reply
 1 5   SetDeviceMode opcode
 2 CARD16   sequence number
 4 0   reply length
 1 CARD8   status
  0  Success
   1 AlreadyGrabbed
  3 + first_error DeviceBusy
 23    unused
```

```
SelectExtensionEvent
 1 CARD8   input extension opcode
 1 6   SelectExtensionEvent opcode
 2 3+n    request length
 4 Window   event window
 2 CARD16   count
 2    unused
 4n LISTofEVENTCLASS desired events
```

```
GetSelectedExtensionEvents
 1 CARD8  input extension opcode
```

```
 1 7  GetSelectedExtensionEvents opcode
 2 2  request length
 4 Window  event window
```

```
 =>
 1 1  Reply
 1 7  GetSelecteExtensionEvents opcode
 2 CARD16  sequence number
 4 n + m    reply length
 2 n       this client count
 2 m       all clients count
 20   unused
 4n LISTofEVENTCLASS this client list
 4m LISTofEVENTCLASS all clients list
```

```
ChangeDeviceDontPropagateList
 1 CARD8   input extension opcode
 1 8   ChangeDeviceDontPropagateList opcode
 2 3+n    request length
 4 Window   event window
 2 n   count of events
 1 mode
  0 AddToList
  1 DeleteFromList
 1    unused
 4n LISTofEVENTCLASS desired events
```

```
GetDeviceDontPropagateList
 1 CARD8  input extension opcode
 1 9  GetDeviceDontPropagateList opcode
 2 2  request length
 4 Window  event window
```

```
 =>
 1 1   Reply
 1 9   GetDeviceDontPropagateList opcode
 2 CARD16   sequence number
 4 n     reply length
 2 n   count of events
 22    unused
 4n LISTofEVENTCLASS don't propagate list
```

```
GetDeviceMotionEvents
 1 CARD8  input extension opcode
 1 10  GetDeviceMotionEvents opcode
 2 4  request length
 4 TIMESTAMP  start
  0 CurrentTime
 4 TIMESTAMP  stop
  0 CurrentTime
 1 CARD8  device id
 3   unused



 =>
 1  1  Reply
 1  10 GetDeviceMotionEvents opcode
 2  CARD16 sequence number
 4  (m+1)n reply length
 4  n  number of DEVICETIMECOORDs in events
 1  m  number of valuators per event
 1  CARD8  mode of the device
   0 Absolute
   1 Relative
 18    unused
 (4m+4)n LISTofDEVICETIMECOORD events



  DEVICETIMECOORD
 4 TIMESTAMP  time
 4m LISTofINT32  valuators



ChangeKeyboardDevice
 1 CARD8  input extension opcode
 1 11  ChangeKeyboardDevice opcode
 2 2  request length
 1 CARD8  device id
 3   unused



 =>
 1 1  Reply
 1 11  ChangeKeyboardDevice opcode
 2 CARD16  sequence number
 4 0  reply length
 1   status
```

```
  0 Success
  1 AlreadyGrabbed
  2 DeviceFrozen
 23   unused



ChangePointerDevice
 1 CARD8  input extension opcode
 1 12  ChangePointerDevice opcode
 2 2  request length
 1 CARD8  x-axis
 1 CARD8  y-axis
 1 CARD8  device id
 1   unused



 =>
 1 1  Reply
 1 12  ChangePointerDevice opcode
 2 CARD16  sequence number
 4 0  reply length
 1   status
  0 Success
  1 AlreadyGrabbed
  2 DeviceFrozen
 23   unused



GrabDevice
 1 CARD8  input extension opcode
 1 13  GrabDevice opcode
 2 5+n   request length
 4 WINDOW  grab-window
 4 TIMESTAMP  time
  0 CurrentTime
 2 n  count of events
 1   this-device-mode
  0 Synchronous
  1 Asynchronous
 1   other-devices-mode
  0 Synchronous
  1 Asynchronous
 1 BOOL  owner-events
 1 CARD8  device id
 2   unused
 4n LISTofEVENTCLASS event list
```

```
 =>
 1 1  Reply
 1 13  GrabDevice opcode
 2 CARD16  sequence number
 4 0  reply length
 1   status
  0 Success
  1 AlreadyGrabbed
  2 InvalidTime
  3 NotViewable
  4 Frozen
 23   unused
```

```
UngrabDevice
 1 CARD8  input extension opcode
 1 14  UngrabDevice opcode
 2 3  request length
 4 TIMESTAMP  time
  0 CurrentTime
 1 CARD8  device id
 3   unused
```

```
GrabDeviceKey
 1 CARD8  input extension opcode
 1 15  GrabDeviceKey opcode
 2 5+n  request length
 4 WINDOW  grab-window
 2 n  count of events
 2 SETofKEYMASK  modifiers
  #x8000 AnyModifier
 1 CARD8  modifier device
  #x0FF UseXKeyboard
 1 CARD8  grabbed device
 1 KEYCODE   key
  0 AnyKey
 1   this-device-mode
  0 Synchronous
  1 Asynchronous
 1   other-devices-mode
  0 Synchronous
  1 Asynchronous
 1 BOOL  owner-events
 2   unused
 4n LISTofEVENTCLASS event list
```

```
UngrabDeviceKey
 1 CARD8  input extension opcode
 1 16  UngrabDeviceKey opcode
 2 4  request length
 4 WINDOW  grab-window
 2 SETofKEYMASK  modifiers
  #x8000 AnyModifier
 1 CARD8  modifier device
  #x0FF UseXKeyboard
 1 KEYCODE   key
  0 AnyKey
 1 CARD8  grabbed device
 3   unused
```

```
GrabDeviceButton
 1 CARD8  input extension opcode
 1 17  GrabDeviceButton opcode
 2 5+n  request length
 4 WINDOW  grab-window
 1 CARD8  grabbed device
 1 CARD8  modifier device
  #x0FF UseXKeyboard
 2 n  count of desired events
 2 SETofKEYMASK  modifiers
 1   this-device-mode
  0 Synchronous
  1 Asynchronous
 1   other-device-mode
  0 Synchronous
  1 Asynchronous
 1 BUTTON  button
  0 AnyButton
 1 BOOL  owner-events
  #x8000 AnyModifier
 2   unused
 4n LISTofEVENTCLASS event list
```

```
UngrabDeviceButton
 1 CARD8  input extension opcode
 1 18  UngrabDeviceButton opcode
 2 4  request length
 4 WINDOW  grab-window
 2 SETofKEYMASK  modifiers
  #x8000 AnyModifier
 1 CARD8  modifier device
  #x0FF UseXKeyboard
 1 BUTTON  button
```

```
  0 AnyButton
 1 CARD8  grabbed device
 3   unused



AllowDeviceEvents
 1 CARD8  input extension opcode
 1 19  AllowDeviceEvents opcode
 2 3  request length
 4 TIMESTAMP  time
  0 CurrentTime
 1   mode
  0 AsyncThisDevice
  1 SyncThisDevice
  2 ReplayThisDevice
  3 AsyncOtherDevices
  4 AsyncAll
  5 SyncAll
 1 CARD8  device id
 2   unused



GetDeviceFocus
 1 CARD8  input extension opcode
 1 20  GetDeviceFocus opcode
 2 2  request length
 1 CARD8  device
 3   unused



 =>
 1 1  Reply
 1 20  GetDeviceFocus opcode
 2 CARD16  sequence number
 4 0  reply length
 4 WINDOW  focus
  0 None
  1 PointerRoot
  3 FollowKeyboard
 4 TIMESTAMP focus time
 1   revert-to
  0 None
  1 PointerRoot
  2 Parent
  3 FollowKeyboard
 15   unused
```

```
SetDeviceFocus
 1 CARD8  input extension opcode
 1 21  SetDeviceFocus opcode
 2 4  request length
 4 WINDOW  focus
  0 None
  1 PointerRoot
  3 FollowKeyboard
 4 TIMESTAMP  time
  0 CurrentTime
 1   revert-to
  0 None
  1 PointerRoot
  2 Parent
  3 FollowKeyboard
 1 CARD8  device
 2   unused
```

```
GetFeedbackControl
 1 CARD8  input extension opcode
 1 22  GetFeedbackControl opcode
 2 2  request length
 1 CARD8  device id
 3   unused
```

```
 =>
 1 1  Reply
 1 22  GetFeedbackControl opcode
 2 CARD16  sequence number
 4 m/4   reply length
 2 n  number of feedbacks supported
 22   unused
 m LISTofFEEDBACKSTATE feedbacks
```

```
  FEEDBACKSTATE KBDFEEDBACKSTATE, PTRFEEDBACKSTATE, INTEGERFEEDBACKSTATE,
  STRINGFEEDBACKSTATE, BELLFEEDBACKSTATE, or LEDFEEDBACKSTATE
```

```
  KBDFEEDBACKSTATE
 1 0  feedback class id
 1 CARD8  id of this feedback
 2 20  length
 2 CARD16  pitch
```

```
2 CARD16  duration
4 CARD32  led_mask
4 CARD32  led_values
1       global_auto_repeat
 0 Off
 1 On
1 CARD8  click
1 CARD8  percent
1       unused
32 LISTofCARD8 auto_repeats
```

```
 PTRFEEDBACKSTATE
1 0  feedback class id
1 CARD8  id of this feedback
2 12  length
2   unused
2 CARD16  acceleration-numerator
2 CARD16  acceleration-denominator
2 CARD16  threshold
```

```
 INTEGERFEEDBACKSTATE
1 0  feedback class id
1 CARD8  id of this feedback
2 16  length
4 CARD32  resolution
4 INT32  minimum value
4 INT32  maximum value
```

```
 STRINGFEEDBACKSTATE
1 1  feedback class id
1 CARD8  id of this feedback
2 4n+8  length
2 CARD16  max_symbols
2 n        number of keysyms supported
4n LISTofKEYSYM  key symbols supported
```

```
 BELLFEEDBACKSTATE
1 1  feedback class id
1 CARD8  id of this feedback
2 12  length
1 CARD8  percent
3   unused
2 CARD16  pitch
```

```
 2 CARD16  duration



  LEDFEEDBACKSTATE
 1 1  feedback class id
 1 CARD8  id of this feedback
 2 12  length
 4 CARD32  led_mask
 4 BITMASK  led_values
  #x0001 On
  #x0002 Off



ChangeFeedbackControl
 1 CARD8  input extension opcode
 1 23  ChangeFeedbackControl opcode
 2 3+n/4  request length
 4 BITMASK  value-mask (has n bits set to 1)
  #x0001 keyclick-percent
  #x0002 bell-percent
  #x0004 bell-pitch
  #x0008 bell-duration
  #x0010 led
  #x0020 led-mode
  #x0040 key
  #x0080 auto-repeat-mode
  #x0001 string
  #x0001 integer
  #x0001 acceleration-numerator
  #x0002 acceleration-denominator
  #x0004 acceleration-threshold
 1 CARD8  device id
 1 CARD8  feedback class id
 2   unused
 n FEEDBACKCLASS



  FEEDBACKCLASS KBDFEEDBACKCTL, PTRFEEDBACKCTL, INTEGERFEEDBACKCTL,
  STRINGFEEDBACKCTL, BELLFEEDBACKCTL, or LEDFEEDBACKCTL



  KBDFEEDBACKCTL
 1 0  feedback class id
 1 CARD8  id of this feedback
 2 20  length
 1 KEYCODE  key
 1   auto-repeat-mode
```

```
 0 Off
 1 On
 2 Default
1 INT8  key-click-percent
1 INT8  bell-percent
2 INT16  bell-pitch
2 INT16  bell-duration
4 CARD32  led_mask
4 CARD32  led_values




 PTRFEEDBACKCTL
1 1  feedback class id
1 CARD8  id of this feedback
2 12  length
2   unused
2 INT16  numerator
2 INT16  denominator
2 INT16  threshold




 STRINGCTL
1 2  feedback class id
1 CARD8  id of this feedback
2 4n+8  length
2   unused
2 n  number of keysyms to display
4n LISTofKEYSYM  list of key symbols to display




 INTEGERCTL
1 3  feedback class id
1 CARD8  id of this feedback
2 8  length
4 INT32  integer to display




 LEDCTL
1 4  feedback class id
1 CARD8  id of this feedback
2 12  length
4 CARD32  led_mask
4 BITMASK  led_values
 #x0001 On
 #x0002 Off
```

```
  BELLCTL
 1 5  feedback class id
 1 CARD8  id of this feedback
 2 8  length
 1 INT8  percent
 3   unused
 2 INT16  pitch
 2 INT16  duration
```

```
GetDeviceKeyMapping
 1 CARD8  input extension opcode
 1 24  GetDeviceKeyMapping opcode
 2 2  request length
 1 CARD8  device
 1 KEYCODE  first-keycode
 1 CARD8  count
 1   unused
```

```
 =>
 1 1  Reply
 1 24  GetDeviceKeyMapping opcode
 2 CARD16  sequence number
 4 nm  reply length (m = count field from the request)
 1 n  keysyms-per-keycode
 23   unused
 4nm LISTofKEYSYM  keysyms
```

```
ChangeDeviceKeyMapping
 1 CARD8  input extension opcode
 1 25  ChangeDeviceKeyMapping opcode
 2 2+nm  request length
 1 CARD8  device
 1 KEYCODE  first-keycode
 1 m  keysyms-per-keycode
 1 n  keycode-count
 4nm LISTofKEYSYM  keysyms
```

```
GetDeviceModifierMapping
 1 CARD8  input extension opcode
 1 26  GetDeviceModifierMapping opcode
```

```
 2 2  request length
 1 CARD8  device
 3   unused
```

```
 =>
 1 1  Reply
 1 26  GetDeviceModifierMapping opcode
 2 CARD16  sequence number
 4 2n  reply length
 1 n  keycodes-per-modifier
 23   unused
 8n LISTofKEYCODE  keycodes
```

```
SetDeviceModifierMapping
 1 CARD8  input extension opcode
 1 27  SetDeviceModifier opcode
 2 2+2n  request length
 1 CARD8  device
 1 n  keycodes-per-modifier
 2   unused
 8n LISTofKEYCODE  keycodes
```

```
 =>
 1 1  Reply
 1 27  SetDeviceModifierMapping opcode
 2 CARD16  sequence number
 4 0  reply length
 1   status
  0 Success
  1 Busy
  2 Failed
 23   unused
```

```
GetDeviceButtonMapping
 1 CARD8  input extension opcode
 1 28  GetDeviceButtonMapping opcode
 2 2  request length
 1 CARD8  device
 3   unused
```

```
 =>
 1 1  Reply
 1 28  GetDeviceButtonMapping opcode
 2 CARD16  sequence number
 4 (n+p)/4  reply length
 1 n  number of elements in map list
 23   unused
 n LISTofCARD8   map
 p   unused, p=pad(n)
```

```
SetDeviceButtonMapping
 1 CARD8  input extension opcode
 1 29  SetDeviceButtonMapping opcode
 2 2+(n+p)/4  request length
 1 CARD8  device
 1 n  length of map
 2   unused
 n LISTofCARD8   map
 p   unused, p=pad(n)
```

```
 =>
 1 1  Reply
 1 29  SetDeviceButtonMapping opcode
 2 CARD16  sequence number
 4 0  reply length
 1   status
  0 Success
  1 Busy
 23   unused
```

```
QueryDeviceState
 1 CARD8  input extension opcode
 1 30  QueryDeviceState opcode
 2 2  request length
 1 CARD8  device
 3   unused
```

```
 =>
 1 1   Reply
 1 30   QueryDeviceState opcode
 2 CARD16   sequence number
 4 m/4   reply length
 1 n         number of input classes
```

```
23    unused
m LISTofINPUTSTATE



 INPUTSTATE KEYSTATE or BUTTONSTATE or VALUATORSTATE



 KEYSTATE
1 CARD8  key input class id
1 36  length
1 CARD8  num_keys
1   unused
32 LISTofCARD8  status of keys



 BUTTONSTATE
1 CARD8  button input class id
1 36  length
1 CARD8  num_buttons
1   unused
32 LISTofCARD8   status of buttons



 VALUATORSTATE
1 CARD8  valuator input class id
1 4n + 4  length
1 n  number of valuators
1   mode
 #x01 DeviceMode (0 = Relative, 1 = Absolute)
 #x02 ProximityState (0 = InProximity, 1 = OutOfProximity)
4n LISTofCARD32  status of valuators



SendExtensionEvent
1 CARD8   input extension opcode
1 31   SendExtensionEvent opcode
2 4 + 8n + m  request length
4 WINDOW   destination
1 CARD8   device
1 BOOL   propagate
2 CARD16   eventclass count
1 CARD8   num_events
3    unused
32n LISTofEVENTS  events to send
4m LISTofEVENTCLASS desired events
```

```
DeviceBell
 1 CARD8  input extension opcode
 1 32  DeviceBell opcode
 2 2  request length
 1 CARD8  device id
 1 CARD8  feedback id
 1 CARD8  feedback class
 1 INT8  percent
```

```
SetDeviceValuators
 1 CARD8  input extension opcode
 1 33  SetDeviceValuators opcode
 2 2 + n  request length
 1 CARD8  device id
 1 CARD8  first valuator
 1 n      number of valuators
 1   unused
 4n LISTofINT32 valuator values to set
```

```
 =>
 1 1   Reply
 1 33   SetDeviceValuators opcode
 2 CARD16   sequence number
 4 0   reply length
 1 CARD8   status
  0 Success
  1 AlreadyGrabbed
 23    unused
```

```
GetDeviceControl
 1 CARD8  input extension opcode
 1 34  GetDeviceControl opcode
 2 2  request length
 2 CARD16  device control type
 1 CARD8  device id
 1   unused
```

```
 =>
 1 1   Reply
 1 34   GetDeviceControl opcode
```

```
 2 CARD16   sequence number
 4 n/4   reply length
 1 CARD8   status
  0   Success
  1   AlreadyGrabbed
  3 + first_error  DeviceBusy
 23    unused
 n    DEVICESTATE
```

```
DEVICESTATE   DEVICERESOLUTIONSTATE
```

```
DEVICERESOLUTIONSTATE
  2 0  control type
  2 8 + 12n  length
  4 n      num_valuators
  4n LISTOfCARD32 resolution values
  4n LISTOfCARD32 resolution min_values
  4n LISTOfCARD32 resolution max_values
```

```
ChangeDeviceControl
  1 CARD8  input extension opcode
  1 35  ChangeDeviceControl opcode
  2 2+n/4  request length
  2 CARD16  control type
  1 CARD8  device id
  1   unused
  n   DEVICECONTROL
```

```
DEVICECONTROL  DEVICERESOLUTIONCTL
```

```
DEVICERESOLUTIONCTL
  2 1  control type
  2 8 + 4n  length
  1 CARD8  first_valuator
  1 n      num_valuators
  2   unused
  4n LISTOfCARD32 resolution values
```

```
=>
 1 1   Reply
 1 35   ChangeDeviceControl opcode
 2 CARD16   sequence number
 4 0   reply length
 1 CARD8   status
  0   Success
  1   AlreadyGrabbed
  3 + first_error  DeviceBusy
 23    unused
```

9+

=+C =+C =+E) =+E)
.',.':)=+A*+'*F
'=+)+!=+A*+*
'=+)+!

```
DeviceValuator
 1 CARD8  code
 1 CARD8  device id
 2 CARD16  sequence number
 2 SETofKEYBUTMASK  state
 1 n  number of valuators this device reports
 1 m  number of first valuator in this event
 24 LISTofINT32 valuators
```

```
DeviceKeyPress
 1 CARD8  code
 1 KEYCODE  detail
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  root
 4 WINDOW  event
 4 WINDOW  child
  0 None
 2 INT16  root-x
 2 INT16  root-y
 2 INT16  event-x
 2 INT16  event-y
 2 SETofKEYBUTMASK  state
 1 BOOL  same-screen
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

```
DeviceKeyRelease
 1 CARD8  code
 1 KEYCODE  detail
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  root
 4 WINDOW  event
 4 WINDOW  child
  0 None
 2 INT16  root-x
 2 INT16  root-y
 2 INT16  event-x
 2 INT16  event-y
 2 SETofKEYBUTMASK   state
 1 BOOL  same-screen
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

```
DeviceButtonPress
 1 CARD8  code
 1 BUTTON  detail
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  root
 4 WINDOW  event
 4 WINDOW  child
  0 None
 2 INT16  root-x
 2 INT16  root-y
 2 INT16  event-x
 2 INT16  event-y
 2 SETofKEYBUTMASK  state
 1 BOOL  same-screen
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

```
DeviceButtonRelease
 1 CARD8  code
 1 BUTTON  detail
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  root
 4 WINDOW  event
 4 WINDOW  child
  0 None
 2 INT16  root-x
 2 INT16  root-y
```

```
 2 INT16  event-x
 2 INT16  event-y
 2 SETofKEYBUTMASK  state
 1 BOOL  same-screen
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

```
DeviceMotionNotify
 1 CARD8  code
 1   detail
  0 Normal
  1 Hint
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  root
 4 WINDOW  event
 4 WINDOW  child
   0 None
 2 INT16  root-x
 2 INT16  root-y
 2 INT16  event-x
 2 INT16  event-y
 2 SETofKEYBUTMASK  state
 1 BOOL  same-screen
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

```
DeviceFocusIn
 1 CARD8  code
 1   detail
  0 Ancestor
  1 Virtual
  2 Inferior
  3 Nonlinear
  4 NonlinearVirtual
  5 Pointer
  6 PointerRoot
  7 None
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  event
 1   mode
  0 Normal
  1 Grab
  2 Ungrab
  3 WhileGrabbed
 1 CARD8  device id
 18   unused
```

```
DeviceFocusOut
 1 CARD8  code
 1   detail
  0 Ancestor
  1 Virtual
  2 Inferior
  3 Nonlinear
  4 NonlinearVirtual
  5 Pointer
  6 PointerRoot
  7 None
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  event
 1   mode
  0 Normal
  1 Grab
  2 Ungrab
  3 WhileGrabbed
 1 CARD8  device id
 18   unused
```

```
ProximityIn
 1 CARD8  code
 1   unused
 2 CARD16  sequence number
 4 TIMESTAMP  time
 4 WINDOW  root
 4 WINDOW  event
 4 WINDOW  child
  0 None
 2 INT16  root-x
 2 INT16  root-y
 2 INT16  event-x
 2 INT16  event-y
 2 SETofKEYBUTMASK   state
 1 BOOL  same-screen
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

```
ProximityOut
 1 CARD8  code
 1   unused
 2 CARD16  sequence number
 4 TIMESTAMP  time
```

```
 4 WINDOW  root
 4 WINDOW  event
 4 WINDOW  child
  0 None
 2 INT16  root-x
 2 INT16  root-y
 2 INT16  event-x
 2 INT16  event-y
 2 SETofKEYBUTMASK   state
 1 BOOL  same-screen
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

=□+□□□□□□□□□A□□□*□□□+□□□□□□'□□□□□□□''□□□□□□□□□□*□□□□□□□□□□□□□F□□□□□□□□□□□□□=□+□□□□C□□□□□□□□A□□□*□□□□□□5□□□□F□□□□□□□□'□□□□=□+□□□□□□)□□□□□□□+□□□□!

```
DeviceStateNotify
 1 CARD8  code
 1 CARD8  device id
  #x80  MORE_EVENTS follow
 2 CARD16  sequence number
 4 TIMESTAMP  time
 1 CARD8  num_keys
 1 CARD8  num_buttons
 1 CARD8  num_valuators
  1 CARD8  valuator mode and input classes reported
   #x01 reporting keys
   #x02 reporting buttons
   #x04 reporting valuators
   #x40 device mode (0 = Relative, 1 = Absolute)
   #x80 proximity state (0 = InProximity, 1 = OutOfProximity)
 4 LISTofCARD8  first 32 keys (if reported)
 4 LISTofCARD8  first 32 buttons (if reported)
 12 LISTofCARD32  first 3 valuators (if reported)
```

```
DeviceKeyStateNotify
 1 CARD8  code
 1 CARD8  device id
  #x80  MORE_EVENTS follow
 2 CARD16  sequence number
 28 LISTofCARD8  state of keys 33-255
```

```
DeviceButtonStateNotify
 1 CARD8  code
 1 CARD8  device id
  #x80  MORE_EVENTS follow
```

```
 2 CARD16  sequence number
 28 LISTofCARD8  state of buttons 33-255
```

```
DeviceValuator
 1 CARD8  code
 1 CARD8  device id
 2 CARD16  sequence number
 2 SETofKEYBUTMASK  state
 1 n  number of valuators this device reports
 1 n  number of first valuator in this event
 24 LISTofINT32 valuators
```

```
DeviceMappingNotify
 1 CARD8  code
 1 CARD8  device id
 2 CARD16  sequence number
 1   request
  0 MappingModifier
  1 MappingKeyboard
  2 MappingPointer
 1 KEYCODE  first-keycode
 1 CARD8  count
 1   unused
 4 TIMESTAMP  time
 20   unused
```

```
ChangeDeviceNotify
 1 CARD8  code
 1 CARD8  id of device specified on change request
 2 CARD16  sequence number
 4 TIMESTAMP  time
 1   request
  0 NewPointer
  1 NewKeyboard
 23   unused
```