X Display Power Management Signaling (DPMS) Extension Protocol Specification

X Project Team Standard

Rob Lembree, Digital Equipment Corporation `<lembree@zk3.dec.com>`

X Display Power Management Signaling (DPMS) Extension Protocol Specification: X Project Team Standard

[illegible]

[illegible]

Table of Contents

Chapter 1. Overview

[illegible][1]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

```
DPMS Extension Power Levels
     0     DPMSModeOn          In use
     1     DPMSModeStandby     Blanked, low power
     2     DPMSModeSuspend     Blanked, lower power
     3     DPMSModeOff         Shut off, awaiting activity
```

[illegible]

[illegible]

---

[1] [illegible]

□□□□□□□□#□□□□□□□'□□□□□□□□□#□□□□□□□:□□□□□□#□□□□□%□□□□□□□□□□□&□□□□□□□&□□□□□□□□□□□□#□□#□"
□□□□□□□□□□□□□#□□□□%□□□&□□□□□'□□□□□□□□ □$□□ □□□□□$□□□□□□□#□□□□□□□'□□□□:%□□□□□□□□□□□□
 □□□□□□ □□□□□□□ □□□□□□□□□$□□□□&□□□□□□□□□□□□□□□□□□□□#□□#□□#□□□□$□□□"□□□□□□□□□□□□$□#□$□$
□□□□□(□□□!-2□□□□□□□□□□□□□□□'□"□□□□$□□□□□□□□□□□#□□□□□□□□□□

Chapter 2. Requests

`DPMSGetVersion`

@A

`DPMSCapable`

@A

`DPMSGetTimeouts`

@A

[illegible]

[illegible]

`DPMSSetTimeouts`

[illegible]

[illegible]

[illegible]

@A

[illegible]

[illegible]

[illegible]

[illegible]

`DPMSEnable`

@A

[illegible]

`DPMSDisable`

@A

[illegible]

`DPMSForceLevel`

[illegible]

@A

[illegible]

`DPMSInfo`

@A

[illegible]

[illegible]

[illegible]

Chapter 3. Events and Errors

=□□□□&□□'□□□□□□□□□□□□□□□□□□□□□$□%□□□$□□□□□□□□□□□□+□□□□□□□□□

Chapter 4. Encoding

!□□□□□□□□□%□□□□□□□□□□1□□□!□□□□#□□□□□#□$□□□□$□# □□□□□□□□□□□□□$□# □□□□□ □□□□#□□'□□□ □□□□□□□□□□□□□□□□□$□□□□□□□

)□□□□□□□□□□%□□□□□□□+□□□□□□□□□□*□!-2*□

```
DPMSGetVersion
     1     CARD8          opcode
     1     0              DPMS opcode
     2     2              request length
     2     CARD16         client_major_version
     2     CARD16         client_minor_version
=>
     1     1              Reply
     1                    unused
     2     CARD16         sequence number
     4     0              length
     2     CARD16         server_major_version
     2     CARD16         server_minor_version
     20                   unused


DPMSCapable
     1     CARD8          opcode
     1     1              DPMS opcode
     2     1              request length
=>
     1     1              Reply
     1                    unused
     2     CARD16         sequence number
     4     0              length
     1     BOOL           capable
     23                   unused


DPMSGetTimeouts
     1     CARD8          opcode
     1     2              DPMS opcode
     2     1              request length
=>
     1     1              Reply
     1                    unused
     2     CARD16         sequence number
     4     0              length
     2     CARD16         standby_timeout
     2     CARD16         suspend_timeout
     2     CARD16         off_timeout
     18                   unused


DPMSSetTimeouts
     1     CARD8          opcode
```

```
     1     3             DPMS opcode
     2     3             request length
     2     CARD16        standby_timeout
     2     CARD16        suspend_timeout
     2     CARD16        off_timeout
     2                   unused
=>


DPMSEnable
     1     CARD8         opcode
     1     4             DPMS opcode
     2     1             request length
 =>


DPMSDisable
     1     CARD8         opcode
     1     5             DPMS opcode
     2     1             request length
 =>


DPMSForceLevel
     1     CARD8         opcode
     1     6             DPMS opcode
     2     2             request length
     2                   power_level
          0     DPMSModeOn
          1     DPMSModeStandby
          2     DPMSModeSuspend
          3     DPMSModeOff
     2                   unused
=>


DPMSInfo
     1     CARD8         opcode
     1     7             DPMS opcode
     2     1             request length
=>
     1     1             Reply
     1                   unused
     2     CARD16        sequence number
     4     0             length
     2                   power_level
           0     DPMSModeOn
           1     DPMSModeStandby
           2     DPMSModeSuspend
           3     DPMSModeOff
     1     BOOL          state
     21                  unused
```