X Synchronization Extension Protocol

X Consortium Standard

Tim Glauert, Olivetti Research/MultiWorks
Dave Carver
Digital Equipment Corporation, MIT/Project Athena
Jim Gettys
Digital Equipment Corporation, Cambridge Research Laboratory
David Wiggins
X Consortium, Inc.

X Synchronization Extension Protocol: X Consortium Standard

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

Table of Contents

Chapter 1. Synchronization Protocol

[illegible]

[illegible]

[illegible]

Description

[illegible]

[illegible] `Counter` [illegible] `Alarm` [illegible]

[illegible] `CreateCounter` [illegible] `Counter` [illegible] `SetCounter` [illegible] `ChangeCounter` [illegible]

[illegible] `System Counters` [illegible]

[illegible] `Alarm` [illegible]

Types

[illegible]

[illegible]

```
INT64:                  64-bit signed integer
COUNTER:                XID
VALUETYPE:              {Absolute,Relative};
TESTTYPE:               {PositiveTransition,NegativeTransition,
                         PositiveComparison,NegativeComparison}
TRIGGER:                [
                         counter:COUNTER,
                         value-type:VALUETYPE,
                         wait-value:INT64,
                         test-type:TESTTYPE
                        ]
WAITCONDITION:          [
                         trigger:TRIGGER,
                         event-threshold:INT64
                        ]
SYSTEMCOUNTER:          [
                         name:STRING8,
                         counter:COUNTER,
                         resolution:INT64
                        ]
ALARM:                  XID
ALARMSTATE:             {Active,Inactive,Destroyed}
```

[illegible] `Counter` [illegible]

[illegible]

[illegible] `Value` [illegible] `Absolute` [illegible] `Relative` [illegible] `Value` [illegible] `None` [illegible] `Relative` [illegible] `Match` [illegible]

[illegible] `PositiveTransition` [illegible] `NegativeTransition` [illegible]

[illegible] PositiveComparison [illegible] NegativeComparison [illegible] None [illegible]

[illegible] Await [illegible] Await [illegible]

[illegible] System- [illegible]

[illegible]

[illegible] Alarm [illegible]

Errors

[illegible]

[illegible]

Requests

[illegible]

```
version-major,version-minor: CARD8
=>
version-major,version-minor: CARD8
```

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

```
=>
system-counters: LISTofSYSTEMCOUNTER
Errors: Alloc
```

[illegible]

[illegible]

```
id: COUNTER
initial-value: INT64
Errors: IDChoice,Alloc
```

[illegible]

[illegible]

```
counter: COUNTER
Errors: Counter,Access
```

[illegible] None [illegible] Counter [illegible] Notify [illegible] Inactive [illegible] AlarmNotify [illegible] Inactive [illegible] Access [illegible] Counter [illegible]

[illegible]

```
counter: COUNTER
=>
value: INT64
Errors: Counter
```

[illegible]

[illegible]

```
wait-list: LISTofWAITCONDITION
Errors: Counter,Alloc,Value
```

[illegible] `SetCounter` [illegible] `ChangeCounter` [illegible] `DestroyCounter` [illegible]

[illegible]

[illegible] `CounterNotify` [illegible] `PositiveTransition` [illegible] `PositiveComparison` [illegible] `CounterNotify` [illegible] `NegativeTransition` [illegible] `NegativeComparison` [illegible] `Counter-Notify` [illegible]

[illegible] `CounterNotify` [illegible] `CounterNotify` [illegible] `CounterNotify` [illegible] `CounterNotify` [illegible]

[illegible]

```
counter: COUNTER
amount: INT64
Errors: Counter,Access,Value
```

[illegible] `CounterNotify` [illegible] `AlarmNotify` [illegible] `Access` [illegible] `Counter` [illegible]

[illegible] Value [illegible]

[illegible]

[illegible]

```
counter: COUNTER
value: INT64
Errors: Counter,Access
```

[illegible]

[illegible]

```
id: ALARM
values-mask: CARD32
values-list: LISTofVALUE
left">Errors: IDChoice,Counter,Match,Value,Alloc
```

[illegible]

[illegible]	[illegible]	[illegible]	
[illegible]	[illegible]	[illegible]	[illegible]
N	N	[illegible]	[illegible]
N	N	[illegible]	1
N	N	[illegible]	[illegible]
[illegible]	[illegible]	,	
[illegible]	E33'	[illegible]	

[illegible]

[illegible] None [illegible] Inactive [illegible]

[illegible] SetCounter, ChangeCounter, DestroyCounter [illegible] ChangeAlarm [illegible] AlarmNotify [illegible]

[illegible] None [illegible] PositiveComparison [illegible] NegativeComparison [illegible] Inactive [illegible] Inactive [illegible] ChangeAlarm [illegible] DestroyAlarm [illegible]

[illegible] PositiveComparison [illegible] PositiveTransition and [illegible] NegativeComparison [illegible] NegativeTransition [illegible] Match [illegible]

[illegible] AlarmNotify [illegible]

[illegible] AlarmNotify [illegible] CreateAlarm [illegible]

[illegible]

```
id: ALARM
values-mask: CARD32
values-list: LISTofVALUE
Errors: Alarm,Counter,Value,Match
```

[illegible] CreateAlarm [illegible] AlarmNotify [illegible] CreateAlarm [illegible]

[illegible]

[illegible]

[illegible]

```
alarm: ALARM
Errors: Alarm
```

[illegible] Destroy [illegible] AlarmNotify [illegible] Destroyed [illegible]

[illegible]

```
alarm: ALARM
=>
trigger: TRIGGER
delta: INT64
events: ALARMEVENTMASK
state: ALARMSTATE
Errors: Alarm
```

[illegible]

[illegible]

```
client-resource: XID
priority: INT32
Errors: Match
```

[illegible]

[illegible]

[illegible]

[illegible]

[illegible]

```
client-resource: XID
=>
priority: INT32
Errors: Match
```

[illegible]

Events

[illegible]

```
counter: COUNTER
wait-value: INT64
counter-value: INT64
time: TIME
count: CARD16
destroyed: BOOL
```

CounterNotify [illegible] Await [illegible]

[illegible] CounterNotify [illegible]

[illegible]

```
alarm: ALARM
counter-value: INT64
alarm-value: INT64
state: ALARMSTATE
time: TIME
```

[illegible] AlarmNotify [illegible] Inactive [illegible] ChangeAlarm [illegible]

Chapter 2. Encoding

[illegible]

[illegible]

Encoding New Types

[illegible]

```
ALARM: CARD32
ALARMSTATE:
       0         Active
       1         Inactive
       2         Destroyed
COUNTER: CARD32
INT64: 64-bit signed integer
SYSTEMCOUNTER:
       4         COUNTER                 counter
       8         INT64                   resolution
       2         n                       length of name in bytes
       n         STRING8                 name
       p                                 pad,p=pad(n+2)
TESTTYPE:
       0         PositiveTransition
       1         NegativeTransition
       2         PositiveComparison
       3         NegativeComparison
TRIGGER:
       4         COUNTER                 counter
       4         VALUETYPE               wait-type
       8         INT64                   wait-value
       4         TESTTYPE                test-type  VALUETYPE:
       0         Absolute
       1         Relative
WAITCONDITION:
       20        TRIGGER                 trigger
       8         INT64                   event threshold
```

[illegible]

Encoding Errors

```
Counter
        1    0            Error
        1    Base + 0     code
        2    CARD16       sequence number
        4    CARD32       bad counter
```

```
        2    CARD16       minor opcode
        1    CARD8        major opcode
        21                unused
Alarm
        1    0            Error
        1    Base + 1     code
        2    CARD16       sequence number
        4    CARD32       bad alarm
        2    CARD16       minor opcode
        1    CARD8        major opcode
        21                unused
```

Encoding Requests

```
Initialize
        1    CARD8        major opcode
        1    0            minor opcode
        2    2            request length
        1    CARD8        major version
        1    CARD8        minor version
        2                 unused
=>
        1    1            Reply
        1                 unused
        2    CARD16       sequence number
        4    0            reply length
        1    CARD8        major version
        1    CARD8        minor version
        2                 unused
        20                unused

ListSystemCounters
        1    CARD8                  major opcode
        1    1                      minor opcode
        2    1                      request length
=>
        1    1                      Reply
        1                           unused
        2    CARD16                 sequence number
        4    0                      reply length
        4    INT32                  list length
        20                          unused
        4n   list of SYSTEMCOUNTER  system counters

CreateCounter
        1    CARD8                  major opcode
        1    2                      minor opcode
        2    4                      request length
        4    COUNTER                id
        8    INT64                  initial value

DestroyCounter
```

```
         1    CARD8                   major opcode
         1    6                       minor opcode’
         2    2                       request length
         4    COUNTER                 counter
=>
         1    1                       Reply
         1                            unused
         2    CARD16                  sequence number
         4    0                       reply length
         8    INT64                   counter value
         16                           unused

Await
         1    CARD8                   major opcode
         1    7                       minor opcodeG
         2    1 + 7*n                 request length
         28n  LISTofWAITCONDITION     wait conditions

ChangeCounter
         1    CARD8                   major opcode
         1    4                       minor opcode0
         2    4                       request length
         4    COUNTER                 counter
         8    INT64                   amount

SetCounter
         1    CARD8                   major opcode
         1    3                       minor opcode/
         2    4                       request length
         4    COUNTER                 counter
         8    INT64                   value

CreateAlarm
         1    CARD8                   major opcode
         1    8                       minor opcode
         2    3+n                     request length
         4    ALARM                   id
         4    BITMASK                 values mask

              #x00000001              counter
              #x00000002              value-type
              #x00000004              value
              #x00000008              test-type
              #x00000010              delta
              #x00000020              events

         4n   LISTofVALUE             values

VALUES
```

[’] [illegible]

[G] [illegible]

[0] [illegible]

[/] [illegible]

```
        4    COUNTER                counter
        4    VALUETYPE              value-type
        8    INT64                  value
        4    TESTTYPE               test-type
        8    INT64                  delta
        4    BOOL                   events

ChangeAlarm
        1    CARD8                  major opcode
        1    9                      minor opcode
        2    3+n                    request length
        4    ALARM                  id
        4    BITMASK                values mask
             encodings as for CreateAlarm
        4n   LISTofVALUE            values
             encodings as for CreateAlarm

DestroyAlarm
        1    CARD8         major opcode
        1    11            minor opcode[L]
        2    2             request length
        4    ALARM         alarm

QueryAlarm
        1    CARD8         major opcode
        1    10            minor opcode[¯]
        2    2             request length
        4    ALARM         alarm
=>
        1    1             Reply
        1                  unused
        2    CARD16        sequence number
        4    2             reply length
        20   TRIGGER       trigger
        8    INT64         delta
        1    BOOL          events
        1    ALARMSTATE    state
        2                  unused

SetPriority
        1    CARD8         major opcode
        1    12            minor opcode
        2    3             request length
        4    CARD32        id
        4    INT32         priority

GetPriority
        1    CARD8         major opcode
        1    13            minor opcode
        2    1             request length
        4    CARD32        id
```

[L] !□□□□□□□□□$□□□□$□□□□□4□□"□$□%□ □□□□□□□□□□□□□□□□□ □□□□□ □□□□□□□□□□□ □%□*

[¯] !□□□□□□□□□$□□□□$□□□□□4□□"□$□%□ □□□□□□□□□□□□□□□□□ □□□□□ □□□□□□□□□□□ □%□*

```
=>
        1     1            Reply
        1                  unused
        2     CARD16       sequence number
        4     0            reply length
        4     INT32        priority
        20                 unused
```

Encoding Events

```
CounterNotify
        1     Base + 0     code
        1     0            kind
        2     CARD16       sequence number
        4     COUNTER      counter
        8     INT64        wait value
        8     INT64        counter value
        4     TIME         timestamp
        2     CARD16       count
        1     BOOL         destroyed
        1                  unused

AlarmNotify
        1     Base + 1     code
        1     1            kind
        2     CARD16       sequence number
        4     ALARM        alarm
        8     INT64        counter value
        8     INT64        alarm value
        4     TIME         timestamp
        1     ALARMSTATE   state
        3                  unused
```